



Release Bulletin 2.3 SP04

SAP Mobile Platform 2.3 SP04

DOCUMENT ID: DC01913-01-0234-02

LAST REVISED: May 2014

Copyright © 2014 by Sybase, Inc. All rights reserved.

This publication pertains to Sybase software and to any subsequent release until otherwise indicated in new editions or technical notes. Information in this document is subject to change without notice. The software described herein is furnished under a license agreement, and it may be used or copied only in accordance with the terms of that agreement.

Upgrades are provided only at regularly scheduled software release dates. No part of this publication may be reproduced, transmitted, or translated in any form or by any means, electronic, mechanical, manual, optical, or otherwise, without the prior written permission of Sybase, Inc.

Sybase trademarks can be viewed at the Sybase trademarks page at <http://www.sybase.com/detail?id=1011207>. Sybase and the marks listed are trademarks of Sybase, Inc. ® indicates registration in the United States of America.

SAP and other SAP products and services mentioned herein as well as their respective logos are trademarks or registered trademarks of SAP AG in Germany and in several other countries all over the world.

Java and all Java-based marks are trademarks or registered trademarks of Oracle and/or its affiliates in the U.S. and other countries.

Unicode and the Unicode Logo are registered trademarks of Unicode, Inc.

All other company and product names mentioned may be trademarks of the respective companies with which they are associated.

Use, duplication, or disclosure by the government is subject to the restrictions set forth in subparagraph (c)(1)(ii) of DFARS 52.227-7013 for the DOD and as set forth in FAR 52.227-19(a)-(d) for civilian agencies.

Sybase, Inc., One Sybase Drive, Dublin, CA 94568.

Contents

Overview	1
Patches Available for SAP Mobile Platform 2.3 SP04 and Later	1
Known Issues for SAP Mobile SDK 2.3 SP04	2
Known Issues with Installing, Uninstalling, and Upgrading	3
Known Issues for SAP Mobile WorkSpace – Mobile Business Object Development	5
Known Issues for SAP Mobile WorkSpace – Hybrid App Package Development	9
Known Issues for Native Object API	14
Create Operation	18
Refresh Operation	19
Known Issues for Hybrid Web Container	20
Known Issues for Hybrid Web Container for Windows Mobile	30
Known Issues for Mobile Devices	36
Known Issues for MAKit	37
Known Issues for OData SDK	38
Documentation Issues and Updates for SAP Mobile SDK	40
Known Issues for SAP Mobile Platform Runtime 2.3 SP04	42
Known Issues with Installing, Uninstalling, and Upgrading	44
Known Issues for Security	54
SQL Anywhere Servers and Utilities Use OpenSSL	55
Known Issues for SAP Mobile Server	57
Known Issues for Agentry Server	68
Known Issues for SAP Control Center	68

- Known Issues for SAP® Data Orchestration Engine
 - Connector72
- Known Issues for Relay Server and Load Balancer75
- Documentation Issues and Updates for SAP Mobile
 - Platform Runtime77
- Obtaining Help and Additional Information78**
 - Technical Support79
 - Downloading Product Updates79
 - Accessibility Features80

Overview

This release bulletin discusses known issues, workarounds, as well as late-breaking documentation updates for SAP® Mobile Platform version 2.3 SP04.

Patches Available for SAP Mobile Platform 2.3 SP04 and Later

SAP® Mobile Platform 2.3 SP04 includes a roll-up of fixes provided as private patches against the earlier releases of Sybase® Unwired Platform.

All private patches provided to customers for various releases prior to January 21, 2014 are included in this Support Package release, and are not individually listed here.

Specific patches delivered after December 1, 2012 that are included in SAP Mobile Platform 2.3 release are:

- Patch_2.0_XXXXXX_729565_1_23_2013
- Patch_2.1_XXXXXX_727937_12_26_2012
- Patch_2.1EBF2_XXXXXX_725528_12_3_2012
- Patch_2.1EBF2_XXXXXX_726835_12_19_2012
- Patch_2.1EBF2_XXXXXX_727059_12_13_2012
- Patch_2.1EBF2_XXXXXX_724840_11_30_2012
- Patch_2.1EBF3_XXXXXX_726851_1_18_2013
- Patch_2.1EBF3_XXXXXX_730099_1_23_2013
- Patch_2.1EBF3_XXXXXX_727650_1_15_2013
- Patch_2.1EBF3_XXXXXX_723863_12_11_2012
- Patch_2.1EBF3_XXXXXX_728872_01_10_2013
- Patch_2.1EBF3_XXXXXX_729846_1_22_2013
- Patch_2.1SP03PL02_XXXXXX_715565_11_28_2012
- Patch_2.1SP03PL02_XXXXXX_725187_722101_12_3_2012
- Patch_2.1SP03PL02_XXXXXX_724345_12_3_2012
- Patch_2.1SP03PL02_XXXXXX_725575_12_11_2012
- Patch_2.1SP03PL02_XXXXXX_716993_12_20_2012
- Patch_2.1SP03PL02_iPhone_719328_12_7_2012
- Patch_2.1SP03PL02_iPhone_1_18_2013
- Patch_2.1SP03PL02_XXXXXX_729103_1_21_2013
- Patch_2.1SP03PL02_XXXXXX_724390_12_4_2012
- Patch_2.1SP03PL02_XXXXXX_727318_12_28_2012

Known Issues for SAP Mobile SDK 2.3 SP04

Specific patches available for SAP Mobile Platform 2.3, and delivered after February 1, 2013 are:

- PATCH_10000_2.1SP03PL02
- PATCH_10001_2.1SP03PL02
- PATCH_10002_2.1SP03PL02
- PATCH_10003_2.1SP03PL02
- PATCH_10004_2.1
- PATCH-10171-2.2SP04
- PATCH-10179-2.2SP04
- PATCH-10180-2.2SP04
- PATCH-10193-2.2SP04
- PATCH-10199-2.2SP04
- PATCH-10201-2.2SP04
- PATCH-10211-2.2SP04
- PATCH-10227-2.2SP04
- PATCH-10229-2.2SP04
- PATCH-10087-2.3SP01
- PATCH-10169-2.3SP01
- PATCH-10186-2.3SP01
- PATCH-10206-2.3SP01
- PATCH-10208-2.3SP01
- PATCH-10210-2.3SP01
- PATCH-10213-2.3SP01
- PATCH-10215-2.3SP01

Note: XXXXXX represents unique names that are not shown explicitly here.

Known Issues for SAP Mobile SDK 2.3 SP04

Learn about known issues and apply workarounds for SAP Mobile SDK.

Key to issue types:

- **RTC** – SAP® Release to Customer tracking number.
- **CSN** – SAP Customer Services Network tracking number.
- **CR** – Sybase® Change Request number.
- **AG** – Agentry® tracking number.
- **N/A** – No tracking number.

Known Issues with Installing, Uninstalling, and Upgrading

Learn about known SDK installation, uninstallation, and upgrade issues, and workarounds for SAP Mobile Platform version 2.3.

See the *SAP Mobile Platform Installation Guide for SAP Mobile SDK* for installation and information regarding the SDK.

Issue #	Description
SMPONP-13011	<p>SAP Mobile Platform version 2.3 SP04 is a shelf replacement of 2.3.</p> <p>The supported installation scenarios for SAP Mobile SDK version 2.3 SP04 are:</p> <ul style="list-style-type: none"> • Existing SAP Mobile SDK 2.3.x installation – 2.3 SP04 is a shelf replacement for 2.3. You can upgrade directly from 2.3.x to 2.3 SP04. • Existing Sybase Unwired Platform SDK 2.2.x – you can install 2.3 SP04 alongside an existing 2.2.x installation, but cannot upgrade a 2.2.x installation. • No existing SDK installation – you can install SAP Mobile SDK version 2.3 SP04 directly.
N/A	<p>Cannot install the Agency server as a Windows service.</p> <p>Beginning in SAP Mobile Platform 2.3 SP02, you cannot install the Agency server as a Windows service.</p> <p>Workaround: None.</p>
SMPONP-11025	<p>After upgrading to version 2.3 SP03, folders are not removed during uninstallation of SAP Mobile SDK.</p> <p>Because of a problem with the uninstaller, when you uninstall the SAP Mobile SDK from a machine by silent installation or uninstallation wizard, the JDK folder is not removed. Additionally, in a Windows Server 2003 environment, when uninstalling the SAP Mobile SDK by silent installation the <code>uninstall</code> folder is also not removed.</p> <p>Workaround: Manually remove the remaining folders after uninstalling.</p>

Issue #	Description
CR-665409	<p>The installation program cannot run in graphical mode.</p> <p>If the HKLM\SOFTWARE\Microsoft\Windows NT\CurrentVersion\AppCompatFlags registry key contains an entry that is the path of the installer binary (for example, C:\setup.exe), you see this error, and the installation fails:</p> <p>The installer is unable to run in graphical mode. Try running the installer with the -console or -silent flag.</p> <p>Workaround: Remove the installer binary path from the HKLM\SOFTWARE\Microsoft\Windows NT\CurrentVersion\AppCompatFlags registry key.</p>
CR-590885	<p>Uninstaller might not run on Windows Vista.</p> <p>Sometimes, the uninstaller does not launch on Windows Vista. This may be caused by the operating system changing the launch command for the SAP Mobile Platform uninstaller, preventing it from using its own JVM to start itself.</p> <p>Workaround: Launch the uninstaller:</p> <pre><jdk_installdir>\java -Dtemp.dir=%TEMP% -jar C:\SMP_HOME\Uninstallers\UnwiredPlatform\uninstall.jar</pre> <p>When you uninstall or cancel out of uninstalling SAP Mobile Platform, the Program Compatibility Assistant shows:</p> <p>This program might not have uninstalled correctly.</p> <p>Select This program uninstalled correctly instead of Uninstall with recommended settings.</p>

Known Issues for SAP Mobile WorkSpace – Mobile Business Object Development

Learn about known issues and apply workarounds for SAP Mobile WorkSpace and mobile business object (MBO) development.

Issue #	Description
SMPONP-7499	<p>Inconsistency between refreshed structures and unrefreshed arguments/client parameters.</p> <p>When multiple MBOs/operations reference the same EIS structure, if the structure changes in the EIS and the MBO Developer refreshes one of the MBOS/operations, the structure is also refreshed in SAP Mobile WorkSpace. But the arguments/client parameters for other MBOs/operations are not refreshed, leading to inconsistency between the structure and the arguments/client parameters that are not refreshed.</p> <p>Workaround: Manually refresh all MBOS/operations that reference the same structure to maintain consistency. This inconsistency does not affect deployment.</p>
SMPONP-5418	<p>Unhandled event loop exceptions may be thrown when the MBO Developer deletes an operation from the mobile application diagram when the Input Mapping tab of the Operation Properties view is open.</p> <p>Workaround: Do not open the Input Mapping tab of the Operation Properties view when deleting an operation from the mobile application diagram.</p>
SMPONP-3086	<p>Deployment fails if a class or interface name in the java.lang package is used as a project package name.</p> <p>Workaround: Change the package name to something not in the java.lang package.</p>

Issue #	Description
N/A	<p><u>When a cache group is defined with an "EIS managed" cache group policy with the "Notify EIS to fetch operation" option selected, if the EIS REST Web service requires authentication, define the credentials during package deployment or from SAP Control Center.</u></p> <p>Workaround: If the Web service pointed to by the REST connection profile requires HTTP authentication, supply the credentials (technical user name and password) either:</p> <ul style="list-style-type: none"> • During package deployment – when deploying the package to the SAP Mobile Server, select the REST Web service connection to which you are mapping, if one exists, or <New Server Connection...> to create a new one from the Server Mapping Connection screen and define the User and Password properties. • From SAP Control Center – any EIS connections defined here, display during package deployment.
RTC-411	<p>SAP Mobile WorkSpace no longer automatically generates client parameter definitions and mappings to operation arguments.</p> <p>Prior to SAP Mobile Platform version 2.2 SP02, SAP Mobile WorkSpace automatically generated client parameter definitions and mappings to operation arguments. In SAP Mobile Platform version 2.2 SP02 and later, when you create a new MBO operation, the client parameter is not automatically created, except for operations of type "Other".</p> <p>Workaround: If the MBO developer wants to map the client parameters to operation arguments, drag and drop the operation argument to the Client Parameters folder in the Input Mapping page in the MBO Operation wizard or Input Mapping tab in the Properties view.</p>
RTC-350	<p>An MBO that is modeled and bound to a data source, then has all attributes deleted from the MBO at a later point, fails to deploy to SAP Mobile Server.</p> <p>Workaround: Use the Bind data source later option to create an MBO that has no attributes.</p>
CR-713043	<p>Foreign key constraint violation error message.</p> <p>You see a foreign key constraint violation error message if you create an MBO by dragging and dropping a table in which the foreign key and the primary key are both "identity" types.</p> <p>Workaround: The MBO is created, and you can safely ignore these error messages.</p>

Issue #	Description
CR-705643	<p>SAP Mobile WorkSpace does not refresh the attributes of a MBO based on a stored procedure after the stored procedure definition has been changed in the EIS.</p> <p>Workaround: After changing the stored procedure definition in the EIS, re-create the JDBC MBO.</p>
CR-703200	<p>MBO operations that include old value arguments that use large object types should be ignored, but SQL clauses still include the old value arguments.</p> <p>SAP Mobile WorkSpace automatically creates an MBO with old value arguments for operations. If the datasource includes operation arguments with large object types (BigString/BigBinary), SAP Mobile WorkSpace shows a warning message that says the old value argument with large object types are ignored, but the SQL definition generated still includes the old value argument with the large object type.</p> <p>Workaround: Manually remove any SQL clauses that include old value arguments with large object types.</p>
CR-689859	<p>The SAP Mobile WorkSpace Welcome page moves to standby mode after Eclipse is started.</p> <p>This is due to a known Eclipse 3.7 bug (https://bugs.eclipse.org/bugs/show_bug.cgi?id=355560). In standby mode, the Welcome page is docked to the right as a view in the Mobile Development perspective, since the Problem view is part of the Mobile Development perspective.</p> <p>Workaround: Double-click the docked Welcome page to extend it to full screen.</p>
CR-689707	<p>Default runtime values requirements.</p> <p>For an MBO operation, a non-nullable argument must get its runtime value from one of the following: client parameter, personalization key, default value, or fill-from-attribute. If a non-nullable argument already uses a fill-from-attribute or client parameter, its default value is ignored. SAP Mobile WorkSpace still allows the user to input a default value.</p> <p>Workaround: In this case, you need not set the default value, because it is not used during runtime.</p>

Issue #	Description
CR-688576	<p>The Oracle datatype NCLOB is not supported.</p> <p>Workaround: Convert the CLOB datatype to a varchar datatype. There are two ways to do this:</p> <ul style="list-style-type: none"> • Create a stored procedure and call it from the MBO. In the stored procedure, convert the CLOBs to varchar: • Create this Transact-SQL® statement, which fetches 4000 bytes of the CLOB: <pre>select dbms_lob.substr(x, 4000, 1) from T.</pre> The maximum varchar length allowed in Transact-SQL statements is 4000 bytes. You can increase this to 32KB. SAP recommends that you use a stored procedure to process the BLOB in this way. For example: <pre>declare my_var long; begin for x in (select X from t) loop my_var := dbms_lob.substr(x.X, 32000, 1);</pre>
CR-676634	<p>For Web Service and other data sources with complex structures and deeply nested element trees, StackOverflow or OutOfMemory messages may occur, or some of the operation input parameters may not be generated properly.</p> <p>In some cases, you see this error:</p> <pre>The assigned stack size and/or heap size is not sufficient for the attempted operation.</pre> <p>Workaround: Increase the stack and heap size of the Eclipse runtime parameter in UnwiredWorkspace.bat with -Xmx, -Xms, -Xss arguments, or reduce the complexity or nested level of the Web Service definition of the MBO operation.</p>
CR-642942	<p>Cannot generate code with Javadoc option enabled to a folder containing Chinese characters.</p> <p>When using the Code Generation wizard, if you enable the option to generate Javadoc, you cannot generate the code to a folder containing Chinese characters without first changing the language for non-Unicode programs to Chinese.</p> <p>Workaround:</p> <ol style="list-style-type: none"> 1. Select Start > Settings > Control Panel. 2. Double-click Regional and Language Options, then click the Advanced tab. 3. From the drop-down list, select Chinese, and click Apply. 4. Click OK.

Known Issues for SAP Mobile WorkSpace – Hybrid App Package Development

Learn about known issues and apply workarounds for SAP Mobile WorkSpace and Hybrid App development.

Issue #	Description
SMPONP-14949	<p>iOS Hybrid App loops infinitely between the HWC screen and Afaria client screen on iOS7 devices, when registering with Afaria.</p> <p>When the "Enable Signing Certificate" option is checked in the Configuration tab for iOS application policies in Afaria server 7.0.4, it may lead to the iOS Hybrid Web Container and Afaria client repeatedly invoking each other.</p> <p>Workaround: Uncheck the Enable Signing Certificate option in the Configuration tab of iOS application policies on the Afaria server.</p>
SMPONP-12758	<p>Keyboard position issue on iOS 7 devices and simulators.</p> <p>The Hybrid App screen does not display well if the soft keyboard was opened and the screen orientation was changed, on iOS7 devices and simulators.</p> <p>Workaround: Close the soft keyboard before changing screen orientation.</p>
SMPONP-3552	<p>64-bit packaging tool cannot be launched on 64-bit Windows.</p> <p>By default, SAP Mobile SDK installer configures the system to use the 32-bit packaging tool. If you try to run the 64-bit packaging tool (<code>Packaging-Tool64.bat</code>) after completing a new or upgrade installation of SAP Mobile SDK on a 64-bit Windows system, launching the tool fails with this message:</p> <p><code>Cannot load 64-bit SWT libraries on 32-bit JVM</code></p> <p>Workaround: Set up a 64-bit JDK to work with the 64-bit packaging tool.</p> <ol style="list-style-type: none"> 1. Set system environment variables <code>CLASSPATH</code>, <code>JAVA_HOME</code>, and <code>Path</code> to point to the 64-bit JDK installed by SAP Mobile Platform at <code>SAP_HOME\MobilePlatform\JDK1.6.0_31-x64</code>. 2. Verify that the <code>SAP_HOME\ObjectAPI\Utils\bin\set-java-home.bat</code> has been modified to point to the installed 64-bit JDK (where <code>SAP_HOME</code> is the installation directory for SAP Mobile SDK on the 64-bit system). 3. Launch <code>PackagingTool64.bat</code>.

Issue #	Description
RTC-333	<p>Updating null values to non-null not supported on Windows Mobile.</p> <p>Null values are not supported for the Windows Mobile platform. For example, the Allows null property in Designer has no effect on a Hybrid Apps running on Windows Mobile devices.</p> <p>Workaround: None.</p>
CR-707123	<p>Cannot upload large image files using the File Manager application on some Android devices.</p> <p>Although image previews and uploads continue to work, you may see this message after selecting an image in a Hybrid App:</p> <p style="background-color: #f0f0f0;">File type is not supported!</p> <p>Workaround: Use a different gallery application by resetting the default:</p> <ol style="list-style-type: none"> 1. Open the Settings application. 2. Click Applications > Manage applications. 3. Click All. 4. Select the current default gallery application. 5. For the Launch by default setting, click Clear defaults.
CR-699341	<p>BlackBerry 7 form labels do not use specified theme.</p> <p>On BlackBerry 7 devices, in a form that uses labels on the left, if the first field is editable, the second label does not initially use the theme set in the form.</p> <p>Workaround: Type in the field to change the label to the appropriate theme.</p>
CR-698779	<p>DatePicker control does not reopen in BlackBerry 7+.</p> <p>In a BlackBerry 7 or later device, if you invoke the DatePicker control in a Hybrid App by clicking in a date field, click Cancel in the DatePicker, and then click again in the same field, the DatePicker control does not reopen.</p> <p>Workaround: After clicking Cancel in the DatePicker, click in another field that is not of type DATETIME or TIME. You can then click in the original date field to open the DatePicker.</p>
CR-694665	<p>AsyncRequestErrorLogs key not generated in a migrated project.</p> <p>If you migrated a Hybrid App project that previously contained a submit Hybrid App action, setting its error screen property does not generate the AsyncRequestErrorLogs list key.</p> <p>Workaround: Create a new Submit Hybrid App action, or click the Generate Error Screen button.</p>

Issue #	Description
CR-690438	<p>A workflow does not initiate an operation.</p> <p>This might happen if the workflow is not constructed correctly.</p> <p>On a Listview details screen, you cannot invoke a submit workflow to invoke an MBO operation that uses child keys of the list key that is bound to that listview. To prevent developers from performing an illegal operation, the keys are removed from the list. However, you can see those keys before making the workflow type operation a Listview details screen because it is not illegal in that circumstance; it is only illegal once you make it a Listview details screen. If you use those keys when it is not a Listview details screen and then make it a Listview details screen, the workflow operation fails without any indication of the problem.</p> <p>Workaround:</p> <p>Client-initiated workflow: verify that no online request operations (such as findall) precede the submit workflow type operation. If there are such operations, remove them.</p> <p>Server-initiated workflow: verify that no links (between the start point and the first screen saved) precede the submit workflow operation. If there are such links, remove them.</p>
CR-684635	<p>Choice controls with a large number of rows do not behave as expected on some platforms.</p> <p>Workaround: For best performance, keep the number of rows in choice controls smaller than 200.</p>
CR-682741	<p>"Validate controls as soon as the user tries to change focus away from them" option in Hybrid App Package generation wizard is not supported on Windows Mobile.</p> <p>Workaround: None.</p>
CR-681918	<p>When you click the Hybrid App icon on iOS devices, you see the message Hybrid App please go to the settings application and enter your configuration....</p> <p>This happens if you attempt to open a version 2.0 workflow on the iOS device and connect to version 2.1 of SAP Mobile Server.</p> <p>Workaround: In SAP Control Center, use the HWC template to create an application connection, and leave the application identifier empty.</p>

Issue #	Description
CR-677684	<p>Locale properties file is not updated if screens, controls, menu items and so on are removed.</p> <p>During Hybrid App package generation, you see a warning that validation keys are missing from the <code><locale>.properties</code> file if the number of screens, controls, or menu items, have changed, for example, if you deleted a menu item. Resource strings associated with screens, controls, and menu items do not correctly update the sequence.</p> <p>Workaround: Either do not remove screens, controls, menu items and so on after localizing, or manually correct the localization <code>.properties</code> file after making the changes.</p>
CR-675904	<p>Object queries in the Online cache group are case-sensitive.</p> <p>If the enterprise information system (EIS) to which an object query is associated with has case-sensitive parameters, the client must pass matching parameters or no data is returned. For example, if the Customer MBO is in an Online cache group, has a load parameter "state" that is propagated to the attribute "state," and a <code>findByParameter</code> object query defined as:</p> <pre>SELECT x.* FROM Customer x WHERE x.state = :state</pre> <p>No data is returned to the client if the user enters <code>state=Ca</code>, since the database parameter is case-sensitive (requiring "CA"). This is not an issue for object queries in other types of cache groups.</p> <p>Workaround: None.</p>

Issue #	Description
CR-674149	<p>Exception received with large amounts of data.</p> <p>When the amount of data is too large to download to the Hybrid App client device, you may get an exception similar to:</p> <pre>"iAnywhere.MobileOffice.AMP.ResponseRetryException" on device, and following error in Workflow- Client.log: 20110616T110249.554 4 My:1 -- ExecuteRequest- > Out 20110616T110249.694 1 iAnywhere.MobileOffice.AMP.Re- sponseRetryException: Exception of type 'iAnywhere.MobileOffice.AMP.ResponseRetryException' was thrown. 20110616T110249.694 1 at Sybase.UnwiredPlat- form.WorkflowClient.Utils.CheckMessageSize (String serializedMessage, ContextData oContextData, Boolean fromResponder) 20110616T110249.694 1 at Sybase.UnwiredPlat- form.WorkflowClient.Responder.ProcessMessageFromDe- vice (ContextData oContextData, String sData, Boolean is- Synchronous) 20110616T110249.694 1 at Sybase.UnwiredPlat- form.WorkflowClient.Responder.ProcessSyncRequest (ContextData oContextData, String sData) 20110616T110249.694 4 My:1 -- ProcessSyncRequest- > Out</pre> <p>Workaround: Increase the allowed maximum message size (SupMaximumMessageLength). From SAP Control Center, expand Hybrid Apps and select the Hybrid App. Select the Context Variables tab. Modify the property.</p>
CR-673572	<p>Hybrid Apps do not work with Android simulators version 2.3.3.</p> <p>See http://code.google.com/p/android/issues/detail?id=12987 for a description of this issue.</p> <p>Workaround: Use an earlier version of the Android simulator. Alternatively, use Android simulator version 4.0 or later.</p>
CR-671242	<p>If a Hybrid App uses a Web Service that takes a structure as its input, submit operation is empty.</p> <p>While you can add items to a listview and save the list, when you submit the operation, it is empty. Array/list fields in structure parameters are not supported. You can have a top-level parameter that is an array/list, and you can have a top-level parameter that is a structure that has non-array/list fields and substructures.</p> <p>Workaround: None.</p>

Issue #	Description
CR-667187	<p>The BlackBerry Bold 9700 device simulator sometimes does not allow the user to have full control of the screen for an application, and may perform the incorrect operations, and return the wrong results. Physical devices work correctly.</p> <p>Workaround: None.</p>

Known Issues for Native Object API

Learn about known issues and apply workarounds for Native Object API and custom development.

Issue #	Description
SMPONP-14989 and SMPONP-15092	<p>BlackBerry clients fail to establish direct mutual HTTPS RBS connections with SAP Mobile Server.</p> <p>In this specific scenario, the server does not return the required "Distinguished Names" in the "Certificates Request" to the BlackBerry client.</p> <p>Workaround: BlackBerry clients using mutual SSL and RBS can connect to SAP Mobile Server through a Relay Server or Apache Proxy Server.</p>
SMPONP-13170	<p>MBO left in inconsistent state, or errors thrown during iOS refresh</p> <p>If an iOS refresh is called on an MBO object before it has been created in the client database, the object may be left in an inconsistent state, or an exception may be thrown.</p> <p>Workaround: Prevent this from occurring by adding code to your application that only calls refresh on an object that was previously created or saved in the database.</p> <ul style="list-style-type: none"> • <i>Create Operation</i> on page 18 • <i>Refresh Operation</i> on page 19
SMPONP-10752	<p>Synchronization via relay server fails with MobiLink communication error (216) if basic auth is enabled for native Object API applications on iOS, Android, WM, and Win32 devices.</p> <p>The cause is that the challenge response is being cached in persistent HTTP.</p> <p>Workaround: From the relay server (IIS) configuration tool, select the Web Site tab and disable persistent HTTP, by unselecting Enable HTTP Keep-Alives.</p>

Issue #	Description
SMPONP-6340	<p>For iOS Object API applications, Code generation (command line and wizard) no longer generates <code>KeyGeneratorPK.m</code> and <code>LocalKey-GeneratorPK.m</code> files, since they are not used.</p> <p>Workaround: Remove any references to these files before compiling your project or you will get compilation errors and build failures.</p>
SMPONP-3552	<p>64-bit packaging tool cannot be launched on 64-bit Windows.</p> <p>By default, SAP Mobile SDK installer configures the system to use the 32-bit packaging tool. If you try to run the 64-bit packaging tool (<code>Packaging-Tool64.bat</code>) after completing a new or upgrade installation of SAP Mobile SDK on a 64-bit Windows system, launching the tool fails with this message:</p> <p>Cannot load 64-bit SWT libraries on 32-bit JVM</p> <p>Workaround: Set up a 64-bit JDK to work with the 64-bit packaging tool.</p> <ol style="list-style-type: none"> 1. Set system environment variables <code>CLASSPATH</code>, <code>JAVA_HOME</code>, and <code>Path</code> to point to the 64-bit JDK installed by SAP Mobile Platform at <code>SUP_HOME\UnwiredPlatform\JDK1.6.0_31-x64</code>. 2. Verify that the <code>SUP_HOME\ObjectAPI\Utils\bin\set-java-home.bat</code> has been modified to point to the installed 64-bit JDK (where <code>SUP_HOME</code> is the installation directory for Sybase Mobile SDK on the 64-bit system). 3. Launch <code>PackagingTool64.bat</code>.
RTC-347	<p>iOS client requests might fail with an HTTP 500 error when using Apache as a reverse proxy.</p> <p>The cause is that Apache implements the HTTP 1.1 specification in such a way that the HTTP header coming from the client, Transfer-Encoding: "Chunked" is not accepted due to the capitalized "c" in "Chunked".</p> <p>Workaround: Change Apache configuration to rewrite incoming HTTP headers. Use <code>mod_headers</code> and add this to the Apache configuration:</p> <pre>RequestHeader edit Transfer-Encoding Chunked chunked early</pre>
RTC-282	<p>Memory warnings from autoreleased objects.</p> <p>You receive memory warnings in your application because of too many autoreleased objects. One example is when there are many objects at the application level through the <code>findAll</code> method.</p> <p>Workaround: To reduce memory growth, use the appropriate autorelease pool. For more information, see this document from Apple: https://developer.apple.com/library/mac/#documentation/Cocoa/Conceptual/MemoryMgmt/Articles/mmAutoreleasePools.html.</p>

Issue #	Description
RTC-280	<p>Failure to start a connection after a shutdown of SAP Mobile Server.</p> <p>For Windows, Windows Mobile, Android and BlackBerry Object API clients, when the device application connects to the Unwired Server, the Unwired Server shuts down, and the device application calls <code>startConnection</code> again immediately after the shutdown occurs, an <code>ApplicationRuntimeEx-ception</code> may be thrown indicating <code>Client state error</code>. Client is already started, without attempting to reconnect to the server.</p> <p>Workaround: You can catch the exception in the device application, sleep a few hundreds of milliseconds, and retry by calling <code>Application.startConnection(timeout)</code> again. After one or two seconds, try to reconnect.</p>
RTC-265	<p>Cannot change the database file path.</p> <p>You create a database for your application with the default database file path, delete the database, and then change the database file path in the connection profile to another value so that you can create a new database file for your application. After you invoke the <code>createDatabase</code> operation again, however, the database is created with the old default database file path, not with the new one.</p> <p>Workaround: None.</p>
RTC-261	<p>When using an Apache server as a reverse proxy without SAP Hosted Relay Server to proxy Object API Applications or HTML5/JS Hybrid Apps against SAP Mobile Server version 2.2 and newer, if a custom URL suffix is used, the client may report connection failures.</p> <p>Workaround: Clients should specify a custom URL suffix including a trailing forward slash <code>"/</code>. For example, <code>"/myApp/"</code> instead of <code>"/myApp"</code></p>
RTC-258	<p>Exception when calling <code>update</code> on a new MBO instance.</p> <p>When you call the <code>update</code> method on a new MBO instance, an <code>ObjectNot-Saved</code> exception is thrown. For example:</p> <pre data-bbox="427 1229 1180 1307">MBO instance = new MBO(); instance.\${UpdateMethod}(); //UpdateMethod is a up- date method defined in the model.</pre> <p>Workaround: Do not call the <code>update</code> method for a new instance. Only call <code>update</code> when creating or saving an instance.</p>

Issue #	Description
RTC-206	<p>Root certificate required for synchronization with an HTTPS server.</p> <p>The Android Object API cannot synchronize with an HTTPS server unless the device has access to the root certificate of the certificate used to sign the certificate presented by the server.</p> <p>Workaround: Use the root certificate on the device.</p>
CR-709353	<p>Cannot pass cookies through personalization keys using replication-based synchronization (RBS).</p> <p>Workaround: Use this code:</p> <pre data-bbox="427 517 1180 621">SUPStringProperties *cookies = [smnwTests cookie-Name]; [[[SUPApplication getInstance] connectionProperties] setHttpCookies:cookies];</pre>
CR-708707	<p>Best practice for deleting the client database.</p> <p>By default, asynchronous operation replay is enabled. When an application is connected (by <code>Application.StartConnection()</code> or <code>Application.RegisterApplication()</code>), it may receive background notifications, and trigger a <code>synchronize</code> or other database operation. If you try to delete the database, you may receive database exceptions.</p> <p>Workaround: Before deleting the database, stop the application connection (<code>Application.StopConnection()</code>).</p>
CR-692374	<p>Enabling compression incurs additional processing on the device and the server side to optimize the amount of data to be transferred over the network.</p> <p>Workaround: Carefully evaluate whether the compression trade-off is appropriate in the deployment environment, and carefully size the server capacity to support it. If appropriate in a particular environment, follow the <i>SAP Mobile Platform Developer Guides</i> to enable compression.</p>

Issue #	Description
CR-690308	<p>The query.getRow() API may not return the correct row to BlackBerry clients.</p> <p>For example, in this connected result set for a BlackBerry client, rs.getRow() may not return the correct value:</p> <pre>Query query = new Query(); query.select("c.id as Id, c.fname as Fname, c.state as countState"); query.from("Customer", "c"); query.setConnectedResultSetEnabled(true); QueryResultSet rs = MyDatabase.executeQuery(query); rs.executeQuery(); rs.last(); rs.afterLast(); rs.previous();</pre> <p>Workaround: Do not use the query.getRow() API QueryResultSet.previous \next return Boolean to indicate if the current position is valid. Rely only on the return value.</p>
CR-675716	<p>SQLite cannot support create operations with more than 3MB of data, which is roughly 128 columns at 64KB per column on Windows Mobile devices.</p> <p>In Windows Mobile applications that use message-based synchronization, when a row reaches 3MB or more, and the client invokes the SQLite create operation during subscription, an internal exception is generated, data import fails, and the import operation fails to commit the transaction.</p> <p>Workaround: None.</p>

Create Operation

The createCreate operation allows the client to create a new record in the local database. To execute a create operation on an MBO, create a new MBO instance, and set the MBO attributes, then call the save() Save() or create() Create() operation. To propagate the changes to the server, call submitPendingSubmitPending.

```
Customer cust = new Customer();
cust.setFname ( "supAdmin" );
cust.setCompany_name( "SAP" );
cust.setPhone( "777-8888" );
cust.create(); // or cust.save();
cust.submitPending();
SMP101DB.synchronize();
// or SMP101DB.synchronize (String synchronizationGroup)
```

```
Customer cust = new Customer();
cust.Fname = "supAdmin";
cust.Company_name = "SAP";
cust.Phone = "777-8888";
```

```
cust.Create();// or cust.Save();
cust.SubmitPending();
```

(void)create

Example 1: Supports create operations on parent entities. The sequence of calls is:

```
SMP101Customer *newcustomer = [[SMP101Customer alloc] init];
newcustomer.fname = @"John";
... //Set the required fields for the customer
[newcustomer create];
[newcustomer submitPending];
[SMP101SMP101DB synchronize];
```

Example 2: Supports create operations on child entities.

```
SMP101Sales_Order *order = [[SMP101Sales_Order alloc] init];
[order autorelease];
//Set the other required fields for the order
order.region = @"Eastern";
order.xxx = yyy;

SMP101Customer *customer = [SMP101Customer find:1008];
[order setCustomer:customer];
[order create];
[order.customer refresh]; //refresh the parent
[order.customer submitPending]; //call submitPending on the parent.
[SMP101SMP101DB synchronize];
```

Note: If refresh is called on an MBO object before it has been created in the client database, the object may be left in an inconsistent state, or an exception may be thrown. Prevent this from occurring by adding code to your application that only calls refresh on an object that was previously created or saved in the database. For example:

```
if (!(mboInstance.isNew))
[mboInstance refresh];
```

Refresh Operation

The refresh operation of an MBO allows you to refresh the MBO state from the client database.

For example:

```
Customer cust = Customer.findById(101);
cust.setFname("newName");
cust.refresh();// newName is discarded
```

```
Customer cust = Customer.FindByPrimaryKey(101);
cust.Fname = "newName";
cust.Refresh();// newName is discarded
```

```
Customer *cust = [Customer findById:101];
cust.fname = @"newName";
[cust refresh]; // newName is discarded
```

Note: If `refresh` is called on an MBO object before it has been created in the client database, the object may be left in an inconsistent state, or an exception may be thrown. Prevent this from occurring by adding code to your application that only calls `refresh` on an object that was previously created or saved in the database. For example:

```
if (!(mboInstance.isNew))
[mboInstance refresh];
```

Known Issues for Hybrid Web Container

Learn about known issues and apply workarounds for Hybrid Web Container (HWC) development.

Issue #	Description
SMPONP-11056	<p>If the Use backwards-compatible API for generation (deprecated) option is selected when generating the Hybrid App with the Hybrid App Designer, the generated UI may look like the iOS style UI even if run on Android and BlackBerry devices.</p> <p>The Use backwards-compatible API for generation (deprecated) option is used to generate JavaScript code using the SUP 2.1.3/2.2 naming convention, i.e. without <code>hwc</code> prefix for all JavaScript functions. These API signatures have been deprecated beginning with SAP Mobile Platform version 2.2 SP02.</p> <p>Workaround: Before generating the Hybrid App:</p> <ol style="list-style-type: none"> 1. Go to the File Order tab in Application properties. 2. Click Restore Default. 3. Manually remove the js files listed in the table which do not exist in the project, such as <code>js/makit/Sybase.MA-22.min.js</code>, and so on.
SMPONP-11047	<p>After filling setting information on an iOS simulator, the Hybrid Web Container displays "Unable to start client engine" and fails to connect to SAP Mobile Server. After filling in the setting information again, Hybrid Web Container connects to the server successfully.</p> <p>When using iOS simulators, you may get the error "Unable to start client engine" when attempting to connect to SAP Mobile Server, after all connection information has been entered correctly in the Settings screen. This only happens on the simulator and not on real devices.</p> <p>Workaround: Enter the connection information again and restart the application on the simulator, or use a real iOS device during development.</p>

Issue #	Description
SMPONP-10777	<p>Android and Blackberry connection failure when using HttpsConnection.</p> <p>Depending on HTTP server behavior, client connection failures may occur when using the https-proxy plugin's HttpsConnection the first time (compared to the browser's default XMLHttpRequest) to send a HTTP(s) request to a remote server. When the client attempts to authenticate itself using basic authentication, failure may occur even when the user name and password are properly set in the header, with the server returning a 401 error.</p> <p>Workaround: Send the request with username and password a second time.</p>
SMPONP-10766	<p>An iOS device loops infinitely between HWC and an Afaria client when trying to use Afaria registration in flight mode.</p> <p>Workaround: None. Keep the device online while performing registration with Afaria.</p>
RTC-387	<p>Sencha Touch 2.1 does not load in the Hybrid Web Container</p> <p>Workaround: Use a Sencha Touch version other than 2.1, such as 2.0.1 or 2.1.1.</p>
RTC-334	<p>If you migrate or otherwise generate a Hybrid App with the Use Backwards Compatible API option set one way, for example, off, and then afterwards change that setting, for example, to on, certain key files, namely <code>API.js</code>, <code>Utils.js</code>, <code>WorkflowMessage.js</code>, and <code>Custom.js</code>, are not regenerated and, thus, use the wrong API setting compared to the other generated files.</p> <p>Workaround: SAP recommends that you decide prior to migration (or, in the case of newly written Hybrid Apps, prior to generation) which API setting you want to use. Failing that, after changing the API setting, manually delete the <code>API.js</code>, <code>Utils.js</code>, <code>WorkflowMessage.js</code>, and <code>Custom.js</code> files and regenerate the Hybrid App with the desired API setting.</p>
RTC-287	<p>On BlackBerry 7 simulators, when a Hybrid App is deployed from the Hybrid App Designer, the simulator fails.</p> <p>See http://forum.jquery.com/topic/jquery-mobile-demo-page-causes-blackberry-7-1-simulator-browser-to-crash for information. This does not happen on an actual device.</p> <p>Workaround: Use a BlackBerry 7 device for deploying Hybrid Apps.</p>

Issue #	Description
RTC-266	<p>JavaScript functions deprecated.</p> <ul style="list-style-type: none"> • <code>showAlertDialog()</code> – the title parameter is no longer used on iOS. It is already ignored on other platforms. This is true only for Sybase Unwired Platform versions 2.1.3 and 2.2 SP02 (2.2.0 and 2.2 SP01 work as before). • <code>showConfirmDialog()</code> – this function does nothing. <p>Workaround:</p> <ul style="list-style-type: none"> • <code>showAlertDialog()</code> – use the native JavaScript <code>alert()</code> function. • <code>showConfirmDialog()</code> – use the native JavaScript <code>confirm()</code> function. <p>Alternatively, you can use PhoneGap APIs to display an alert or confirmation dialog. Although the PhoneGap APIs allow you to set the title of the alert and confirmation dialogs, and buttons, the APIs are asynchronous, so you cannot use them as a direct substitute for the <code>showAlertDialog()</code> unless you refactored the code in each instance where it is used.</p>
RTC-240	<p>On Android, PhoneGap Media play function does not play sound when the source is a Web server. This is a known PhoneGap issue and is fixed in PhoneGap (Cordova) version 2.1.0 so that sound files that are stored on the device play correctly.</p> <p>Workaround: Include the sound files with the application. See the discussion about this problem at:</p> <p>https://groups.google.com/forum/?fromgroups=#!topic/phonegap/xCOWgKh0IQ0</p>
RTC-236	<p>When a 2.1.3 or older client tries to connect to a 2.2 or newer server using an invalid URL suffix (such as '/'), the client receives an HTTP authentication challenge and the connection fails.</p> <p>Workaround: Use a valid URL suffix when attempting to connect a 2.1.3 or older client to a 2.2 or newer server.</p>
RTC-220	<p>In a page of the Hybrid App, the Save or Submit Hybrid App action fails to save the credential information to the local store by providing only the "credential cached user name" without a corresponding "credential cached password."</p> <p>Workaround: Use the <code>hwc.saveLoginCredentials()</code> JavaScript API to save the user name.</p>

Issue #	Description
RTC-205	<p>On BlackBerry Torch and Storm devices, when using the Camera API, any picture taken is always rotated 90 degrees to the right.</p> <p>Workaround: None. This is a known problem with RIM APIs on these devices. See https://www.blackberry.com/jira/browse/JAVAAPI-701 (requires a login) and http://supportforums.blackberry.com/t5/Java-Development/Storm-Torch-camera-getSnapshot-orientation-issue/td-p/1316867.</p>
RTC-171	<p>If a password is used for automatic device registration using the <code>hwc . saveSettings ()</code> API, the password is used only once and is not saved in the Hybrid Web Container.</p> <p>Upon successful automatic registration, subsequent connections to the server uses the userid+deviceid+authcode combination (the password is not required). This is by design.</p> <p>Workaround: To save the password in the application, do so in the application code with the secured storage <code>SUPStorage</code> API.</p>
RTC-169	<p>Using the Hybrid Web Container on older BlackBerry devices may result in warnings or errors from the operating system, such as The memory available on your device is low. Close some of the items below.</p> <p>Workaround: Run the BlackBerry Hybrid Web Container on newer OS 6.x or OS 7.x devices with more memory. There is no fix available from RIM for Java-based platforms. See the following Blackberry sites, which require a login. https://www.blackberry.com/jira/browse/JAVAAPI-2275.</p>
RTC-139	<p>iOS issue in opening apps and messages with the Javascript Metadata API .</p> <p>On iOS, when using the JavaScript API functions (<code>hwc . openApp</code> and <code>hwc . openMessage</code>) that allow the user to open a Hybrid App or message from within another Hybrid App, when opening the Hybrid App from within another application, the previously opened application closes. On platforms other than iOS, when the user closes the newly opened application, the previously opened application is still open.</p> <p>Workaround: None.</p>
RTC-135	<p>On BlackBerry 5.0, the HTML5 sessionStorage object is not supported.</p> <p>On both <code>window.open ()</code> and <code>window.location.href</code> the HTML5 sessionStorage values are not carried to the next page.</p> <p>Workaround: None.</p>

Issue #	Description
RTC-115	<p>Cannot update prepackaged Hybrid Apps.</p> <p>The version number of the new Hybrid App must be later than the current version number.</p> <p>Workaround: Edit the <code>manifest.xml</code> file to update the version number and repackage the Hybrid App files.</p>
RTC-111	<p>On Android devices, when attempting to upload log files from the Hybrid Web Container after re-registering the device user, an Upload Failed message is returned periodically.</p> <p>Workaround: Upload the log files again.</p>
RTC-91	<p>In Hybrid Apps running on iOS devices, when a user enters a string in a numeric field, no error message is given, which allows the user to incorrectly enter string data in a numeric field.</p> <p>In Hybrid Apps running on iOS, numeric edit boxes do not validate user entries.</p> <p>Workaround: None.</p>
RTC-90	<p>On all Hybrid Web Container device platforms, when an expired certificate is used for device registration, the error message is MMS Authentication Failed, which does not indicate the root cause of the error.</p> <p>Workaround: Make sure your certificate is not expired.</p>
RTC-73	<p>On all platforms, in manual registration mode, after calling the <code>hwc.saveSettings</code> API in <code>hwc-api.js</code>, the client cannot connect to the server.</p> <p>Workaround: To connect to the server by manual registration, call the <code>hwc.startClient</code> API after the <code>hwc.saveSettings</code> invocation.</p>

Issue #	Description
RTC-53	<p>On iOS, some APIs, such as SUPStorage, perform slowly when using WiFi with an HTTP proxy.</p> <p>This happens only when all of the following conditions are true:</p> <ul style="list-style-type: none"> • The Hybrid Web Container experiences long (10 - 75 seconds) delays while processing the JavaScript of Hybrid Apps and navigating between screens. • The Hybrid Web Container is running on a device connecting to the network through WiFi. • The WiFi access point is using a network HTTP proxy (Settings > WiFi > Choose a Network > HTTP Proxy). <p>If all of these conditions are true, these workarounds are available depending upon whether the Hybrid App is using JavaScript generated by the Hybrid App Forms Designer or using the Packaging Tool in conjunction with the JavaScript container code that ships with SAP Mobile Platform 2.2.</p> <p>Workaround #1: If you are using the JavaScript files generated by the Hybrid App Forms Designer, you must edit <code>API.js</code>, <code>SUPStorage.js</code>, and <code>Utils.js</code>, which are located in the <code>html/js</code> directory of the generated application code. For each file:</p> <ol style="list-style-type: none"> 1. Search for POST. Each instance is within a function, and typically there is a unique code path per platform. 2. Identify the <code>isIOS()</code> code branch where an <code>xmlHttpRequest</code> is being opened, and change the last parameter of the open function call for the <code>xmlHttpRequest</code> to change it from <code>false</code> to <code>true</code>. For example, in <code>SUPStorage.js</code>, change line 171 from: <pre>xmlHttpReq.open("POST", "/sup.amp?querytype=work-flowstorage&" + versionURLParam, false);</pre> to: <pre>xmlHttpReq.open("POST", "/sup.amp?querytype=work-flowstorage&" + versionURLParam, true);</pre> <p>Note: If you are deploying the Hybrid App to multiple platforms, make sure these changes affect only the iOS code path, which might mean creating a new “elseif” clause.</p> <ol style="list-style-type: none"> 3. Regenerate the Hybrid App package. <p>Workaround #2: Modify <code>hwc_api.js</code> (usually installed in <code>SMP_HOME\UnwiredPlatform\MobileSDK<version>\HybridApp\Container</code>) in the Hybrid App to look like the following example, and redeploy the application to the Hybrid Web Container.</p> <pre>/** * Encapsulate the HTTP post method. This function * is called internally */</pre>

Issue #	Description
	<pre> hwc.postDataToContainer = function(queryType, data) { try { var response = ""; if (hwc.isWindowsMobile()) { xmlhttp = hwc.getXMLHttpRequest(); xmlhttp.open("POST", "/sup.amp?querytype=" + queryType + "&" + hwc.versionURLParam, false); xmlhttp.send(data); response = xmlhttp.responseText; } else if (hwc.isAndroid()) { response = _HWC.postData("http:// localhost/sup.amp?querytype=" + queryType + "&" + hwc.versionURLParam, data); } else if (hwc.isBlackBerry()) { var xmlhttp = hwc.getXMLHTTPPre- quest(); xmlhttp.open("POST", "http://localhost/sup.amp?querytype=" + quer- yType + "&" + hwc.versionURLParam, false); xmlhttp.send(data); response = xmlhttp.response- Text; } else if (hwc.isIOS()) { var xmlhttp = hwc.getXMLHTTPPre- quest(); xmlhttp.open("POST", "http://local- host/sup.amp?querytype=" + queryType + "&" + hwc.ver- sionURLParam, true); try { xmlhttp.send(data); } catch (ex) { if (ex.message.search(/XMLHttpRe- quest Exception 101/) == -1) { throw ex; } } } return response; } catch (ex) </pre>

Issue #	Description
	<pre> { hwc.log("hwc.postDataToContainer error: " + ex.message, "ERROR", false); } }; </pre>
RTC-52	<p>A Hybrid App fails to deploy to the device.</p> <p>If the SAP Mobile Platform is installed in a cluster, and different paths are used on each application service node, the Hybrid App log may contain a message similar to Updated failed for Hybrid App item. SAP Mobile Platform currently assumes that application service nodes are installed in the same path on all the nodes in the cluster, that is, that all application server nodes are installed in the same path on all cluster nodes. It stores full paths in the database during Hybrid App package installation. When the client connects, it looks for those paths in the file system. If the node it is connecting to does not have one of those paths, you see the error.</p> <p>Workaround: Install SAP Mobile Platform using the same installation path for each node of the cluster.</p>
RTC-51	<p>iOS Hybrid Web Container fails when an Afaria client is not setup for seeding.</p> <p>If you do not provision the Afaria server with the iOS Hybrid Web Container seeding file, and if the Afaria iOS client is installed on the iOS device and not configured with the connection settings in the iOS Hybrid Web Container, the Hybrid Web Container fails upon start-up. This happens because the Hybrid Web Container launches the Afaria client application to get the seeding file (settings) that can be used to connect to the Afaria server. The Afaria client application fails before relaunching the iOS Hybrid Web Container.</p> <p>Workaround: If you do not provision the Afaria server with the iOS Hybrid Web Container seeding file, the user must manually enter the connection settings for the Hybrid Web Container before launching it.</p> <p>This issue does not occur if the Afaria client is not installed on the iOS device.</p>
RTC-37	<p>On Android 3.x devices, when proxy is enabled on the WiFi connection, connecting to SAP Mobile Server directly using the HTTPS protocol makes the Hybrid Web Container client fails.</p> <p>This is an Android bug. See http://code.google.com/p/android/issues/detail?id=37050 for details.</p> <p>Workaround: Either turn off the proxy or connect through SAP Relay Server.</p>

Issue #	Description
CR-708173	<p>When the Hybrid Web Container tries to retrieve data from the MBO package, an <code>Invalid application id <***></code> for package error appears.</p> <p>Workaround: In SAP Control Center, manually add an application ID for the MBO package's application list.</p> <ol style="list-style-type: none"> 1. Log in to SAP Control Center. 2. Go to <code>hostname@localhost > Applications</code> and click the Applications tab. 3. Click Properties. 4. In Domains and Packages, select the domain that contains the applicable MBO package. 5. Assign the application ID to the MBO's package's applications list.
CR-705895	<p>After adding JavaScript code in the <code>customAfterMenuItemClick</code> method to update the check box (using JQuery Mobile) state on the screen, the check-box fails to update.</p> <p>Workaround: When you use JavaScript to update the check box (using JQueryMobile) value, you must also add the refresh code. For example:</p> <p>Whole sample in "customAfterMenuItemClick" method of Custom.js</p> <pre>function customAfterMenuItemClick(screen, menuItem) { if (screen === "Start" && menuItem === "setCheck- box") { var checkbox1 = document.getElement- ById('checkbox1'); checkbox1.checked = true; var checkbox2 = document.getElement- ById('checkbox2'); checkbox2.checked = false; if (isJQueryMobileLookAndFeel) { \$("input[type='checkbox']").checkboxra- dio("refresh"); } } }</pre>

Issue #	Description
CR-705219	<p>When the iOS Hybrid Web Container application tries to retrieve seeding information from an Afaria iOS App store hosted package you see this error message: Afaria client application is installed but not configured.</p> <p>Workaround: Configure Afaria client application and try again or go to the Settings application and enter your configuration information.</p> <ul style="list-style-type: none"> • Seed Enterprise-hosted packages on the Afaria server. • Manually configure the connection information.
CR-703883	<p>Switching from one edit box to another on a BlackBerry 7.0 simulator or device using the touch screen or mouse requires two clicks or touches.</p> <p>Workaround: None for BlackBerry 7.0. Upgrading to BlackBerry 7.1 eliminates the problem.</p>
CR-702603	<p>BlackBerry 7.0 users see a white screen until the Workflow application's activation screen opens. See https://www.blackberry.com/jira/browse/JAVAA-PI-119. Note this URL requires a login.</p> <p>Workaround: None.</p>
CR-693907	<p>Hybrid Web Container occasionally fails on Android 2.2.</p> <p>This can happen when all of these conditions are present:</p> <ul style="list-style-type: none"> • There is only one read-only edit box control on a single screen, and • The application is using jQueryMobile GA version, and • You are using an Android 2.2 simulator or Samsung Galaxy device with Android 2.2. <p>Workaround:</p> <ul style="list-style-type: none"> • Upgrade the OS on the device to Android 2.3, or, • If using an Android 3.x simulator, see CR 673572, or, • Add one or more controls to the screen.
CR-691005	<p>Image upload may fail on BlackBerry 6 simulators older than version 6.0.0.499.</p> <p>Workaround: Use a BlackBerry 9800 simulator with version 6.0.0.499 or later.</p>

Issue #	Description
CR-686465	<p>Camera feature is supported on some device simulators/emulators.</p> <ul style="list-style-type: none"> • iOS - not supported. • Android 2.2 - not supported. See http://code.google.com/p/android/issues/detail?id=9376. • BlackBerry - supported. • Windows Mobile - supported; however, can photograph only a grey/black screen. <p>Workaround: Use a physical device.</p>
CR-680253	<p>Images do not appear correctly on mobile devices.</p> <p>Hybrid Web Container/Workflow applications can display pictures from binary enterprise information system (EIS) data. But when a MBO developer drags and drops a table that contains an image field to create the MBO, the image field maps to a Binary datatype that has a length of approximately 3KB, which may not be large enough for the entire image. At runtime, the binary data of the image may be truncated in the cache database (CDB), and appear incorrectly on the device.</p> <p>Workaround: When creating the MBO, manually modify the length of the binary field to make sure it is large enough to hold the image binary data, or use the BigBinary datatype instead.</p>

Known Issues for Hybrid Web Container for Windows Mobile

Learn about known issues and apply workarounds for Hybrid Web Container (HWC) development for Windows Mobile.

Issue #	Description
RTC-300	<p>On Windows Mobile, calling a save or submit action to a persisted cached password causes the Hybrid Web Container to crash if the Hybrid Web Container was not registered to Unwired Server.</p> <p>Workaround: Register the Windows Mobile device to Unwired Server before saving credential information to the device.</p>
RTC-236	<p>When a 2.1.3 or older client tries to connect to a 2.2 or newer server using an invalid URL suffix (such as '/'), the client receives an HTTP authentication challenge and the connection fails.</p> <p>Workaround: Use a valid URL suffix when attempting to connect a 2.1.3 or older client to a 2.2 or newer server.</p>

Issue #	Description
RTC-222	<p>After loading Hybrid Web Container JavaScript files (for example, datajs), a memory leak occurs.</p> <p>Within a closure code, when adding a new window property that references an object, the object is not correctly identified as garbage collection (GC) after closing the Hybrid App.</p> <p>For example, the datajs-1.0.3.js file contains a code pattern:</p> <pre>(function (window, undefined) { if (!window.OData) { window.OData = {}; } var odata = window.OData; odata.defaultHttpClient = { request: function () { xhr = new ActiveXObject("Micro- soft.XMLHTTP"); } }; })(this);</pre> <p>When exiting the Hybrid App, window.OData still occupies the memory. After the Hybrid App is opened and closed several times, an "Out of Memory" error occurs.</p> <p>Workaround: Manually release the object. For example, add "window.OData = null;" in the hwc.close() function that is invoked when exiting the Hybrid App. Add these lines in hwc.close() to avoid the memory leak:</p> <pre>//datajs if (window.datajs) { window.ActiveXObject = window.oldActiveXObject; window.datajs = null; window.OData = null; window.oldActiveXObject = null; } //hwc window.CallbackSet = null; window._Picture = null; //cordova window.console = null; window.PhoneGap = null; window.Cordova = null; window.plugins = null; window.addEventListener = null; window.removeEventListener = null;</pre> <p>On Windows Mobile, if you experience a memory leak under these conditions, restart the device.</p>
RTC-220	<p>In a page of the Hybrid App, the Save or Submit Hybrid App action fails to save the credential information to the local store by providing only the "credential cached user name" without a corresponding "credential cached password."</p> <p>Workaround: Use the hwc.saveLoginCredentials() JavaScript API to save the user name.</p>

Issue #	Description
RTC-197	<p>On Windows Mobile, when changing between landscape and portrait orientation, the spinner disappears.</p> <p>Workaround: None.</p>
RTC-171	<p>If a password is used for automatic device registration using the <code>hwc . save - Settings ()</code> API, the password is used only once and is not saved in the Hybrid Web Container.</p> <p>Upon successful automatic registration, subsequent connections to the server uses the <code>userid+deviceid+authcode</code> combination (the password is not required). This is by design.</p> <p>Workaround: To save the password in the application, do so in the application code with the secured storage <code>SUPStorage</code> API.</p>
RTC-156	<p>On Windows Mobile 6.0, if you use the task manager to end the Hybrid Web Container process, you cannot restart the Hybrid Web Container.</p> <p>Workaround: Do not end the Hybrid Web Container process on Windows Mobile 6.0. It works as expected on Windows Mobile 6.5.</p>
RTC-147	<p>On Windows Mobile, when using the Media Cache function, <code>hwc . MediaC - cache . getUrl ()</code>, a large media resource, such as an image, may not appear correctly if the user opens and closes the Hybrid App frequently.</p> <p>Workaround: None.</p>
RTC-115	<p>Cannot update prepackaged Hybrid Apps.</p> <p>The version number of the new Hybrid App must be later than the current version number.</p> <p>Workaround: Edit the <code>manifest . xml</code> file to update the version number and repackage the Hybrid App files.</p>
RTC-93	<p>On Windows Mobile, the <code>removeMenuItem ()</code> JavaScript API in <code>API . js</code> does not work.</p> <p>Workaround: None.</p>
RTC-90	<p>On all Hybrid Web Container device platforms, when an expired certificate is used for device registration, the error message is <code>MMS Authentication Failed</code>, which does not indicate the root cause of the error.</p> <p>Workaround: Make sure your certificate is not expired.</p>
RTC-88	<p>After changing the default Hybrid App in SAP Control Center, invoking the Hybrid Web Container on Windows Mobile devices does not automatically open the new default Hybrid App.</p> <p>Workaround: After changing the default Hybrid App in SAP Control Center, restart the device.</p>

Issue #	Description
RTC-73	<p>On all platforms, in manual registration mode, after calling the <code>hwc . save-Settings</code> API in <code>hwc-api . js</code>, the client cannot connect to the server.</p> <p>Workaround: To connect to the server by manual registration, call the <code>hwc . startClient</code> API after the <code>hwc . saveSettings</code> invocation.</p>
RTC-52	<p>A Hybrid App fails to deploy to the device.</p> <p>If the SAP Mobile Platform is installed in a cluster, and different paths are used on each application service node, the Hybrid App log may contain a message similar to <code>Updated failed for Hybrid App item</code>. SAP Mobile Platform currently assumes that application service nodes are installed in the same path on all the nodes in the cluster, that is, that all application server nodes are installed in the same path on all cluster nodes. It stores full paths in the database during Hybrid App package installation. When the client connects, it looks for those paths in the file system. If the node it is connecting to does not have one of those paths, you see the error.</p> <p>Workaround: Install SAP Mobile Platform using the same installation path for each node of the cluster.</p>
RTC-49	<p>On Windows Mobile devices and emulators, Cordova cannot play audio files.</p> <p>Workaround: None.</p>
CR-708173	<p>When the Hybrid Web Container tries to retrieve data from the MBO package, an <code>Invalid application id <***> for package</code> error appears.</p> <p>Workaround: In SAP Control Center, manually add an application ID for the MBO package's application list.</p> <ol style="list-style-type: none"> 1. Log in to SAP Control Center. 2. Go to <code>hostname@localhost > Applications</code> and click the Applications tab. 3. Click Properties. 4. In Domains and Packages, select the domain that contains the applicable MBO package. 5. Assign the application ID to the MBO's package's applications list.

Issue #	Description
CR-708122	<p>Native application on Windows Mobile device receives an error, Can't find an Entry Point 'DLL_setMclCallbacks' in a PInvoke DLL 'CMessagingClient.dll.</p> <p>This can occur if a 2.1.2 (or older) version of the Hybrid Web Container (HWC) is installed on the same device as a native application using the Sybase Unwired Platform 2.1.3 libraries. The HWC and native applications share a common CMessagingClient.dll.</p> <p>Workaround: In order for a 2.1.2 (or older) HWC and a 2.1.3 native app to coexist and both successfully run on the same Windows Mobile device, install only the 2.1.3 version of CMessagingClient.dll, and load it into memory on the device. Before starting either version of the application, verify that older versions of that DLL are removed from the device.</p>
CR-705895	<p>After adding JavaScript code in the customAfterMenuItemClick method to update the check box (using JQuery Mobile) state on the screen, the checkbox fails to update.</p> <p>Workaround: When you use JavaScript to update the check box (using JQueryMobile) value, you must also add the refresh code. For example:</p> <p>Whole sample in "customAfterMenuItemClick" method of Custom.js</p> <pre>function customAfterMenuItemClick(screen, menuItem) { if (screen === "Start" && menuItem === "setCheckbox") { var checkbox1 = document.getElementById('checkbox1'); checkbox1.checked = true; var checkbox2 = document.getElementById('checkbox2'); checkbox2.checked = false; if (isJQueryMobileLookAndFeel) { \$("input[type='checkbox']").checkboxradio("refresh"); } } }</pre>

Issue #	Description
CR-693381	<p>Cannot preview a selected picture On Windows Mobile emulator.</p> <p>When using the <code>imageElement.src = imageUri</code> in the <code>getPicture</code> function, you cannot preview the selected image on the Windows Mobile emulator. This is because the HTML browser adds an unexpected prefix to the URI, so the Hybrid Web Container cannot find the file to which the URI refers.</p> <p>Workaround:</p> <ul style="list-style-type: none"> • Preview the image using an actual device instead of the emulator, or, • Assign image data instead of an image URI to the image element so the image data can be retrieved through the JavaScript API.
CR-688399	<p>On Windows Mobile devices, thumbnails do not show properly if an image has a large size..</p> <p>The root cause is that Internet Explorer cannot load a large image; try one of these solutions to address the image size:</p> <p>Workaround #1: Specify a small-sized image as the thumbnail instead of using the original large image, for example:</p> <pre data-bbox="366 765 1174 869"></pre> <p>Workaround #2: Pass the width and height as the parameters in the source of the image control, so the container compresses the original image on the fly, for example:</p> <pre data-bbox="366 956 1174 1060"></pre> <p>The width and height parameters are supported only on Windows Mobile and may cause display issues on other platforms.</p>
CR-686465	<p>Camera feature is supported on some device simulators/emulators.</p> <ul style="list-style-type: none"> • iOS - not supported. • Android 2.2 - not supported. See http://code.google.com/p/android/issues/detail?id=9376. • BlackBerry - supported. • Windows Mobile - supported; however, can photograph only a grey/black screen. <p>Workaround: Use a physical device.</p>

Issue #	Description
CR-680253	<p>Images do not appear correctly on mobile devices.</p> <p>Hybrid Web Container/Workflow applications can display pictures from binary enterprise information system (EIS) data. But when a MBO developer drags and drops a table that contains an image field to create the MBO, the image field maps to a Binary datatype that has a length of approximately 3KB, which may not be large enough for the entire image. At runtime, the binary data of the image may be truncated in the cache database (CDB), and appear incorrectly on the device.</p> <p>Workaround: When creating the MBO, manually modify the length of the binary field to make sure it is large enough to hold the image binary data, or use the BigBinary datatype instead.</p>

Known Issues for Mobile Devices

Learn about known issues and apply workarounds for various mobile devices.

Issue #	Description
RTC-87	<p>When the Windows Mobile emulator is uncradled then cradled again, the first attempt to retrieve data from the server fails.This happens only on the emulator.</p> <p>Workaround: The subsequent request succeeds.</p>
RTC-85	<p>Windows Mobile devices fail with a the connection template is not found message when there are multiple application connection templates with the same App ID but different security configurations, trying to register.</p> <p>Workaround: You must append the specific security configuration to the user name in this format: user@securityconfig.</p> <p>The user name field in the Windows Mobile Hybrid Web Container settings screen is disabled when the registration type is Certificate. Enable it by building a customized container using the template source code.</p>
RTC-43	<p>On Windows 7 virtual machines, the Windows Mobile emulator cannot connect to Windows Mobile Device Center.</p> <p>Workaround: When using Windows 7, do not use a virtual machine to run the Windows Mobile emulator.</p>

Known Issues for MAKit

Learn about known issues and apply workarounds for MAKit development.

Issue #	Description
N/A	<p>When opening a MAKit PDF from the Product Documentation Web site, some users may be prompted to update Adobe Flash Player.</p> <p>When some users attempt to open the MAKit Developer Guides at http://sybooks.sybase.com/sybooks/sybooks.xhtml?id=1289&c=firsttab&a=0&p=categories, they may get an error stating an updated version of Flash is required to view the PDF package.</p> <p>Workaround: Update to the most recent version of both Adobe Reader and Adobe Flash Player by visiting the Adobe Downloads Web site at http://www.adobe.com/downloads/.</p>
RTC-137	<p>Orientation issues when running MAKit 2.2 code example in the iOS6.0 iPad Device.</p> <p>When the iPad's orientation changes from portrait to landscape or vice versa, the MAKit code example's orientation does not change.</p> <p>Workaround: Follow these steps:</p> <ol style="list-style-type: none"> 1. In the MAKitCodeExamplesAppDelegate, replace this line: <pre>[self.window addSubview:navController.view];</pre> with this line: <pre>[self.wndow setRootViewController:navController];</pre> 2. In the MAKitCodeExamples-info.plist file, delete the sub items (item 0 and item 1) under Supported interface orientations.
CR-703197	<p>SUPContainer iOS (iPad) what-if integer columns turns blank after clearing the value.</p> <p>When the MAKit what-if feature is used in the SAP Mobile Platform Workflow container environment on iOS (iPad devices), the <code>what-if</code> integer column becomes blank and the slider does not reposition when the value is cleared using device keyboard input and the user taps out of the field. This field should have a value of 0 after clearing and the slider control should be synchronized to the 0 position.</p> <p>Workaround: Users can use the slider control to change the what-if column values.</p>

Known Issues for OData SDK

Learn about known issues and apply workarounds for the OData SDK.

Issue #	Description
SMPONP-11143	<p>The HTTP channel returns a 404 error when a request URL includes ".jsp".</p> <p>The HTTP channel returns a 404 error when a request URL includes ".jsp". For example, <i>http://supServer:8000/ProxyEndpoint/backendFile.jsp?para1=val1&para2=val2</i></p> <p>Workaround: In the <i>SMP_HOME\deploy\webapps\httpchannel\WEB-INF\web.xml</i> file, replace:</p> <pre data-bbox="422 604 1180 704"><servlet-mapping> <servlet-name>JspServlet</servlet-name> <url-pattern>*.jsp</url-pattern> </servlet-mapping></pre> <p>with:</p> <pre data-bbox="422 765 1180 866"><servlet-mapping> <servlet-name>DispatcherServlet</servlet-name> <url-pattern>*.jsp</url-pattern> </servlet-mapping></pre>

Issue #	Description
RTC-328	<p>Relay Server: Server response containing header with empty value is considered malformed.</p> <p>When there is a PUT request passing through Relay Server to a SAP Mobile Platform proxy connection, you get an error message 400 - Bad request with no response from back end server. The root cause is whenever the GW server receives an HTTP request with an empty value in the header (for example, below HttpResponse contains the header key Vary and its values are empty), this issue occurs.</p> <p>Example</p> <pre> ~~~~~A sample respond message header~~~~~ HTTP/1.1 204 No Content Expires: Thu, 01 Jan 1970 00:00:00 GMT Set-Cookie: X-SUP-APPCID=283ec655-deaf-4ae6-8fe7-92dbbca4cf2f Date: Fri, 18 Jan 2013 01:49:19 GMT Vary: Content-Encoding: Cache-Control: no-cache, no-store, no-transform X-AUSERNAME: zxiong X-ASESSIONID: lchn8gf Set-Cookie: atlassian.xsrf.token=BOC2-AB74-RK7A-C5C b5297c7d951949fea3f91ccdd7025ff61c7e434c lin; Path=/ X-Seraph-LoginReason: OK Set-Cookie: JSESSIONID=4A49B145411AE327021EE424EDB0B4F3; Path=/; HttpOnly X-AREQUESTID: 1069x403945x1.... </pre> <p>Workaround: None.</p>
RTC-155	<p>Push notification does not work with any security configuration other than "admin" for certificate-based mutual SSL authentication.</p> <p>If you use any other security configuration, you get an error message 403 - User not in required role.</p> <p>Workaround: Use single SSL with any security configuration or use "admin" as the security configuration for mutual SSL to enable Push notifications.</p>

Documentation Issues and Updates for SAP Mobile SDK

Read about updates, corrections, and clarifications to the documentation released with SAP Mobile Platform Mobile SDK.

Issue #	Description
N/A	<p>The topic <i>Adding References to a Mobile Application Project</i> located in <i>Developer Guide: Windows and Windows Mobile Object API Applications > Development Task Flow for DOE-based Object API Applications > Creating a Project</i> contains references to incorrect DLLs.</p> <p>The correct DLLs for DOE-based Object API applications for these steps are:</p> <ol style="list-style-type: none"> 1. Add the following libraries for the appropriate device platform as references in the Visual Studio project: <ul style="list-style-type: none"> • Windows Mobile – <ul style="list-style-type: none"> • sup-client.dll – from SMP_HOME\MobileSDK<version>\ObjectAPI\DOE\WM • Bouncycastle.dll – from SMP_HOME\MobileSDK<version>\ObjectAPI\DOE\WM • Windows – <ul style="list-style-type: none"> • sup-client.dll – from SMP_HOME\MobileSDK<version>\ObjectAPI\DOE\Win32 • Bouncycastle.dll – from SMP_HOME\MobileSDK<version>\ObjectAPI\DOE\Win32 • ECTrace.dll – from SMP_HOME\MobileSDK<version>\ObjectAPI\DOE\Win32 2. Add the following libraries for the appropriate device platform as items in the Visual Studio project. Set "Build Action" to Content and "Copy to Output Directory" to Copy always: <ul style="list-style-type: none"> • Windows Mobile – CMessagingClient.<version>.dll – from SMP_HOME\MobileSDK<version>\ObjectAPI\DOE\WM\PocketPC or SMP_HOME\MobileSDK<version>\ObjectAPI\DOE\WM\Smartphone • Windows – <ul style="list-style-type: none"> • CMessagingClient.<version>.dll – from SMP_HOME\MobileSDK<version>\ObjectAPI\DOE\Win32 • TravelerLib.dll – from SMP_HOME\MobileSDK<version>\ObjectAPI\DOE\Win32 • zlib1.dll – from SMP_HOME\MobileSDK<version>\ObjectAPI\DOE\Win32

Issue #	Description
SMPONP-15863	<p>Agentry Toolkit in SAP Mobile Platform 2.3 SP04 PL01 supports developing iOS 7 applications with Xcode 5.1 and iOS 7 SDK.</p> <p>For more information:</p> <ul style="list-style-type: none"> • <i>Supported Hardware and Software > Agentry Applications – Supported Versions > Apple iOS Versions for Agentry Applications</i> • <i>Developer Guide: Migrating to SAP Mobile SDK 2.3 SP04 > Migrate Agentry Applications > Porting Agentry Applications to iOS 7 Look and Feel</i>
SMPONP-15268	<p>Statically linked Sqlite Encryption Extension (SEE) for WM/Win32 DOE/ MBS makes references to SQLite.Interop.065.dll and System.Data.SQLite.dll redundant.</p> <p>Ignore references in the documentation to SQLite.Interop.065.dll and System.Data.SQLite.dll. These topics still contain references - <i>Developer Guide: Windows and Windows Mobile Object API Applications > Development Task Flow for DOE-based Object API Applications > Creating a Project</i>:</p> <ul style="list-style-type: none"> • <i>Client Application Dependencies</i> • <i>Adding References to a Mobile Application Project</i> • <i>Creating a Project in Visual Studio</i>
SMPONP-11248	<p>Object API Application Tutorials not updated for 2.3 SP04</p> <p>Only the <i>Tutorial: iOS Object API Application Development</i> is updated in the 2.3 SP04 release. The following tutorials have not been updated for SAP Mobile Platform version 2.3 SP04, and contain references to previous versions of SAP Mobile Platform. However the tutorials are still valid for 2.3 SP04:</p> <ul style="list-style-type: none"> • <i>Tutorial: Hybrid App Package Development > Developing a Hybrid App Package</i> • <i>Tutorial: Windows Mobile Object API Application Development > Developing a Windows Mobile Device Application > Creating the User Interface for the Windows Mobile Device Application</i> • <i>Tutorial: BlackBerry Object API Application Development > Developing a BlackBerry Application > Creating the BlackBerry Project</i> • <i>Tutorial: Windows Mobile Object API Application Development > Developing a Windows Mobile Device Application</i> <hr/> <p>Note: For SAP Mobile Platform version 2.3 SP03 and above, tutorials that reference UltraliteJ files, use UltraLiteJ16 instead of UltraLiteJ12.</p>

Issue #	Description
CR-710608	<p>onHttpCommunicationError returns an unexpected code.</p> <p>In an environment configured for SiteMinder authentication, the expectation is that onHttpCommunicationError is called back for error condition 302. This condition is not currently fulfilled by the Windows and Windows Mobile platforms; instead, they return 404 errors.</p> <p>Workaround: None.</p>

Known Issues for SAP Mobile Platform Runtime 2.3 SP04

Learn about known issues and apply workarounds for SAP Mobile Platform Runtime components.

Key to issue types:

- **RTC** – SAP® Release to Customer tracking number.
- **CSN** – SAP Customer Services Network tracking number.
- **CR** – Sybase® Change Request number.
- **AG** – Agentry® tracking number.
- **N/A** – No tracking number.

Issue #	Description
SMPONP-11603	<p>Certicom software, which provides cryptography services for securing storage and transmission of sensitive information, is no longer supported by SAP Sybase products. These services have been replaced by alternate providers, as indicated in the documentation for each SAP Sybase product.</p> <p><i>See SQL Anywhere Servers and Utilities Use OpenSSL on page 55.</i></p>
RTC-113	<p>Login fails when the value of the "tm_max_no" parameter in the SAP® EIS is less than the number of users concurrently logged in.</p> <p>The value of the tm_max_no parameter in the SAP EIS limits the maximum number of active logins. If the number of concurrent users logged in is larger than this value, SAP Mobile Server shows a R3_LOGIN_FAILED error.</p> <p>Workaround: Increase the value of the tm_max_no parameter in the SAP EIS to a suitable value.</p>

Issue #	Description
CR-717585	<p>When assigning a personalization key using binary datatype to an operation argument or load argument with BigBinary type, if the data in the personalization key exceeds 35K, the server throws exceptions during synchronization:</p> <pre data-bbox="422 343 1180 442">[LNSupController+Finalize.m:61] Send data Exception- SUPPersistenceException: SUPPersistenceException from synchronize: -- SUPSynchronizeException: logi- nFail, Sync failed: -1497 (ERROR) %1:4 %2:4000</pre> <p>Workaround: When a binary personalization is assigned to an operation argument or a load argument, its size cannot exceed 35K. Additionally, do not map a personalization key to big object types such as BigString or BigBinary. The length of all personalization key values combined is a maximum of 64,000 bytes. Binary values are base64 encoded, so their length must be multiplied by 1.5 to account for encoding overhead.</p>
CR-714679	<p>SAP Control Center stops responding and shows Connecting with the SCC Managed Object Server message after login.</p> <p>Workaround: Instead of using the standard URL (<code>https:// < host-name > :8283/scc</code>), if you are accessing SAP Control Center from the same host, use <code>https://localhost:8283/scc</code> or <code>https:// < host name.domain > :8283/scc</code>.</p> <p>Alternatively, try accessing SAP Control Center from a remote machine.</p>

Known Issues with Installing, Uninstalling, and Upgrading

Learn about known runtime installation, uninstallation, and upgrade issues and workarounds.

Issue #	Description
SMPONP-15390	<p>When upgrading from 2.2 SPx to 2.3.x, if you have a Microsoft Cluster shared host installation with the data tier databases and db log files split into separate locations, some of the registry information for the separate database and log file locations are not preserved when the registry location is moved from HKLM\SOFTWARE\Wow6432Node\Sybase to HKLM\SOFTWARE\Wow6432Node\SAP, which causes problems with later upgrades.</p> <p>Workaround: Immediately after upgrading, update the registry by adding these expanded string values to HKLM\SOFTWARE\Wow6432Node\SAP\Mobile-Platform\2.3:</p> <ul style="list-style-type: none">• CDBDataFolder = %cdb location%• CDBLogFolder = %cdb log location%• CLDBDataFolder = %clusterdb location%• CLDBLogFolder = %clusterdb log location%• DDBDataFolder = %domainlogdb location%• DDBLogFolder = %domainlogdb log location%• MDBDataFolder = %monitordb location%• MDBLogFolder = %monitordb log location%

Issue #	Description
SMPONP-15347	<p>Errors in secondary server node log after installing 2.3 SP04 cluster.</p> <p>After performing these steps:</p> <ol style="list-style-type: none"> 1. Install the Data Tier. 2. Install the Primary app node with autostart=true. 3. Install the Secondary app node with autostart=false. 4. Install a Scale-out node. 5. Deploy packages and start the Secondary node. <p>An error similar to this appears in the server node log:</p> <pre>WARN MMS main [com.sybase.sup.server.mbs.SUPPackageUtil] [] [] No scope named [d1_onlineproject.1_0] exists at location [C:\S-_.123456781\MobilePlatform012345678901\Servers\UnwiredServer\bin\..\deploy\sup]. java.lang.RuntimeException: No scope named [d1_onlineproject.1_0] exists at location [C:\S-_.123456781\MobilePlatform012345678901\Servers\UnwiredServer\bin\..\deploy\sup].</pre> <p>Workaround: The “No scope named [d1_onlineproject.1_0] exists..” error occurs when new packages are deployed to the secondary node while the secondary node is starting but has not yet synchronized. Restart the secondary node to synchronize the packages.</p>
SMPONP-15095	<p>Cannot upgrade Sybase Unwired Platform version 2.1 with DOE-C installed to SAP Mobile Platform version 2.3 SP04.</p> <p>Workaround: Delete these registry entries before upgrading to SAP Mobile Platform version 2.3 SP04:</p> <pre>HEKY_LOCAL_MACHINE\SOFTWARE\Wow6432Node\Sybase\UnwiredPlatform\2.1; HEKY_LOCAL_MACHINE\SOFTWARE\Wow6432Node\Sybase\UnwiredPlatform\2.2;</pre>
SMPONP-14182	<p>Performing an uninstallation from the GUI after performing a 2.3 to 2.3 SP04 upgraded installation, generates database related errors.</p> <p>These errors are related to the upgrade in SAP Mobile Platform from SQLAnywhere version 12 to SQLAnywhere version 16, for example:</p> <pre>remove32BitCDB.err remove32BitCLDB.err remove32BitMonDB.err removeCDB.err removeCLDB.err</pre> <p>Workaround: These errors can be ignored.</p>

Issue #	Description
SMPONP-13514	<p>Some registry keys are not automatically removed after uninstalling SAP Mobile Platform version 2.3 SP04.</p> <p>These registry keys are not deleted on 64-bit platforms after a 2.3 SP04 runtime uninstallation:</p> <pre> HKEY_LOCAL_MACHINE\SOFTWARE\ODBC\ODBC.INI\monitordb HKEY_LOCAL_MACHINE\SOFTWARE\ODBC\ODBCINST.INI \SCC-3_2 HKEY_LOCAL_MACHINE\SOFTWARE\ODBC\ODBCINST.INI\SQL Anywhere 16 HKEY_LOCAL_MACHINE\SOFTWARE\Sybase\SQL Anywhere\16.0 </pre> <p>Workaround: These registry keys can be ignored. You can remove these keys manually, but it is not necessary.</p>
SMPONP-4639	<p>Double-clicking desktop icon fails to launch SAP Mobile Platform command on Windows 8 and Windows 2012.</p> <p>SAP Mobile Platform on Windows 8 and 2012 fails to run a silent uninstallation, start or stop SAP Mobile Server, or run the upgrade script by double clicking the corresponding desktop icon.</p> <p>Workaround: Start the command by navigating to the appropriate folder, right-clicking the file of interest (for example, SilentUninstall_Win.bat and selecting Run as administrator.</p>
SMPONP-13011	<p>SAP Mobile Platform Runtime version 2.3 SP04 is a shelf replacement of 2.3.</p> <p>When installing SAP Mobile Platform Runtime version 2.3, it is version 2.3 SP04. When upgrading from version 2.3 (any SP), you can install version 2.3 SP04 directly, and do not need to upgrade incrementally.</p> <p>The installer can directly upgrade your Sybase Unwired Platform 2.2.x or SAP Mobile Platform version 2.3.x installation to SAP Mobile Platform version 2.3. SP04. If you have a version of Sybase Unwired Platform earlier than 2.2.x, additional steps are required to upgrade to SAP Mobile Platform Runtime version 2.3. SP04</p>

Issue #	Description
SMPONP-11220	<p>A cluster node fails to start because other nodes were in an abnormal state.</p> <p>Error messages similar to these in the bootstrap log file are an indication of this problem:</p> <pre>2013-09-17 23:07:18.694 INFO MMS main [com.sybase.sup.cache.impl.CacheService] [] [] Members of distributed cache: [/10.172.157.69, / 10.172.157.72, /10.172.180.46] 2013-09-17 23:07:18.694 INFO MMS main [com.sybase.sup.cache.impl.CacheService] [] [] Expected members: [10.172.180.46, 10.172.180.47, 10.172.157.69, 10.172.157.72]</pre> <p>In this case, the mismatch node (10.172.180.47) indicates an abnormal status, and one in which the node does not start.</p> <p>Workaround: Restart the problematic node.</p>

Issue #	Description
SMPONP-11042	<p>Error retrieving packages while resynchronizing in the server log.</p> <p>After upgrading from SAP Mobile Platform version 2.3 to 2.3 SP03, if you find the following errors in the server log, perform one of the workarounds.</p> <pre> 2013-09-10 11:20:02.100 INFO DOEC sup.mbs.3 [com.sybase.vader.djc.jms.DSMessageListener] [] [] (sup.mbs.3) com.sybase.vader.djc.jms.DSMessageListener.onMessage:104 - Invoking DataServices with package name: d2_sap_crm.1_0 2013-09-10 11:20:02.842 ERROR MMS Thread-156 [com.sybase.sup.admin.server.DOEServerStatusUpdateTask] [] [] Error retrieving packages while resynchronizing. com.sybase.sup.doec.admin.DOECAdminException at com.sybase.sup.doec.admin.impl.DOECAdminImpl.sendDOECMessage(DOECAdminImpl.java:779) at com.sybase.sup.doec.admin.impl.DOECAdminImpl.resyncPackage(DOECAdminImpl.java:372) at com.sybase.sup.admin.server.DOEServerStatusUpdateTask.resyncPackages(DOEServerStatusUpdateTask.java:74) at com.sybase.sup.admin.server.DOEServerStatusUpdateTask.run(DOEServerStatusUpdateTask.java:28) at sun.reflect.NativeMethodAccessorImpl.invoke0(Native Method) at sun.reflect.NativeMethodAccessorImpl.invoke(NativeMethodAccessorImpl.java:57) at sun.reflect.DelegatingMethodAccessorImpl.invoke(DelegatingMethodAccessorImpl.java:43) at java.lang.reflect.Method.invoke(Method.java:601) at com.sybase.djc.server.ServiceComponent.runService(ServiceComponent.java:469) at com.sybase.djc.server.ServiceComponent_DJC.runService(ServiceComponent_DJC.java:203) </pre> <p>Workaround 1: Manually modify the Servers\UnwiredServer\Repository\Package\d{domainId}\sup\components\d{domainId}_{packageName}\{packageVersion}.properties file to input the techuser-password property value as plain text, and restart the server.</p> <p>Workaround 2: Update the password in SAP Control Center:</p> <ol style="list-style-type: none"> 1. Select localhost@localhost (running) > Domains >{your domain}-> Connections. 2. Select the connection in the connections list. 3. Click the Properties button. 4. Update the user name and password, and save.

Issue #	Description
SMPONP-10775	<p>Visual C 2005 installation log error in SMPUpgrade . log when upgrading Development and Test (DT) edition of SAP Mobile Platform from version 2.3 to 2.3 SP03.</p> <p>The actual error codes returned during the upgrade are:</p> <pre>ERROR: return value: 3010</pre> <p>and:</p> <pre>ERROR: VC Runtime 2005 failed.</pre> <p>Workaround: You can safely ignore these errors. Return code from running vcredist indicates that the installation was successful and requires a system restart.</p>
SMPONP-10112	<p>After installing a cluster, and upgrading from version 2.3 SP02 to 2.3 SP03, the error removeDataTierServices.err appears in the silent Install log.</p> <p>These errors may appear in the silent install log after the upgrade:</p> <pre>The service has not been started. Error stopping service "SAPMobilePlatformConsolidatedDatabase". The service has not been started. Error stopping service "SAPMobilePlatformClusterDatabase". The service has not been started. Error stopping service "SAPMobilePlatformMonitorDatabase".</pre> <p>Workaround: You can safely ignore these errors.</p>
SMPONP-10094	<p>Server node fails to upgrade to version 2.3.3 as the Messaging Server upgrade fails.</p> <p>This issue happens when you place the installation image on a mapped network drive. The installation requires the image to be placed on a local drive.</p> <p>Workaround: Move the upgrade scripts to the local drive. Re-run the scripts.</p>

Issue #	Description
SMPONP-4059	<p>Error message after upgrade</p> <p>After upgrading a cluster installation to 2.3 SP03, the following error message appears in SMP_HOME\SCC-3_2\sccRepoPwdChange\supA-TUpgrade.log for each Application Node:</p> <pre> 2013-01-27 18:38:34,815 [INFO] [main] (SCCRepositoryPwdUpdater.java:29) - Begin database password update. 2013-01-27 18:39:48,245 [ERROR] [main] (SCCRepositoryPwdUpdater.java:45) - ASAEngine: The "scc_repository" dataserver Engine could not be started java.lang.Exception: ASAEngine: The "scc_repository" dataserver Engine could not be started at com.sybase.sup.sysadmin.asa.ASAEngine.startEngine(ASAEngine.java:145) at com.sybase.sup.sysadmin.sccconfig.SCCRepositoryASAInstance.startEngine(SCCRepositoryASAInstance.java:36) at com.sybase.sup.sysadmin.sccconfig.SCCRepositoryASAInstance.open(SCCRepositoryASAInstance.java:29) at com.sybase.sup.sysadmin.sccconfig.apps.repoPwdUpdate.SCCRepositoryPwdUpdater.update(SCCRepositoryPwdUpdater.java:32) at com.sybase.sup.sysadmin.sccconfig.apps.SCCRepositoryPwdUpdate.main(SCCRepositoryPwdUpdate.java:28) </pre> <p>Workaround: Ignore the error message. This error does not have any functional impact.</p>
RTC-397	<p>QueueNotReadyException appears in <i>server1</i> log</p> <p>A QueueNotReadyException appears in <i>server1</i> log when installing SAP Mobile Platform with primary install <i>node1</i> and secondary <i>node2</i>, but starting <i>node2</i> before <i>node1</i>.</p> <p>Workaround: Ensure <i>node1.properties</i> appears in the SMP_HOME/repository/Instance/com/sybase/djc/server/ApplicationServer folder, then restart <i>node1</i>.</p>

Issue #	Description
RTC-393	<p>The SAP Mobile Platform 2.3 installer waits unnecessarily long when upgrading from Sybase Unwired Platform 2.2.X to SAP Mobile Platform 2.3</p> <p>Workaround 1: Workaround 1: When upgrading your 2.2.X installation to 2.3, set the startup mode for Sybase Unwired Platform services to automatic before running the SAP Mobile Platform 2.3 installer</p> <p>Workaround 2: If the 2.3 installer was started without setting the Sybase Unwired Platform services startup mode to automatic, and the installer status displays Pinging server using the secure management port . . . for a long time, then the upgrade has completed normally. At this point, the installer can be stopped manually using Windows Task Manger.</p>
RTC-363	<p>Potential locked file may cause upgrade to fail.</p> <p>When upgrading, there is a potential problem with a process holding a lock on one of the 12 Adaptive Server Anywhere (ASA) libraries (DLLs), even though all the ASA processes have shut down. This causes the upgrade to fail because the upgrade cannot overwrite the file.</p> <p>Workaround:</p> <ol style="list-style-type: none"> 1. Shut down all SAP Mobile Platform processes. 2. If services were set to automatic, set the start-up for the SAP Mobile Platform services to manual. 3. Restart the system. 4. Run the upgrade after the system has restarted. 5. If step 2 was performed prior to upgrade, set the start-up for the services back to automatic. <hr/> <p>Note: This is an issue when upgrading from 2.2.X to 2.3.X using the GUI installer.</p>
RTC-360	<p>Backing up the SAP Mobile Platform Runtime installation fails because the SAP Control Center path is too long.</p> <p>The path to the Embedded Web Container in the SCC-3_2 folder is too long for Windows to process.</p> <p>Workaround: Before backing up the SAP Mobile Platform Runtime installation, you must delete the contents of <i>SMP_HOME\services\Embedded-WebContainer\container\Jetty-7.6.2.v20120308\work</i>. Delete the contents of this folder from the command prompt, and not from Windows Explorer.</p> <hr/> <p>Note: For more information, see <i>SAP Note 1835740: Backup of SAP Mobile Platform Runtime</i>, which requires an SAP Market Place login.</p>

Issue #	Description
RTC-318	<p>Installation or upgrade cannot continue host name of system resolves to local link address.</p> <p>In a new or upgrade installation, the installer displays this error message:</p> <p>The host name of the system resolves to a local link address. This suggests an incorrect binding order of network adapters. The install/upgrade cannot proceed. Once the binding order is corrected, restart the installer. Click OK to exit the installer.</p> <p>The upgrade version of the message displays the "local link address" in parentheses.</p> <p>Explanation: If no usable IP addresses are available on the system where you are installing SAP Mobile Platform, Windows assigns a "local link" IP address in the range 169.254.0.0/16. The installer detects that the system's IP address is only usable locally, and stops.</p> <p>Workaround: Execute the commands below from the command prompt, restart the server, and restart the installer.</p> <pre> netsh interface ipv6 set prefix ::1/128 50 5 netsh interface ipv6 add prefix ::1/128 50 5 netsh interface ipv6 set prefix ::1/96 40 4 netsh interface ipv6 add prefix ::1/96 40 4 netsh interface ipv6 set prefix ::ffff:0:0/96 30 3 netsh interface ipv6 add prefix ::ffff:0:0/96 30 3 netsh interface ipv6 set prefix ::/0 20 2 netsh interface ipv6 add prefix ::/0 20 2 netsh interface ipv6 add prefix ::ffff: 169.254.0.0/112 10 1 netsh interface ipv6 set prefix ::ffff: 169.254.0.0/112 10 1 </pre>
RTC-306	<p>During the first start of a cluster, the secondary node cannot start because the primary node is bound to an unreachable address.</p> <p>Rarely, during the first start of the first node of a cluster, the cluster configuration cache binds itself erroneously to an IP address that cannot be reached by secondary nodes in the cluster. When this happens, the secondary nodes appear to stop responding during installation (if the primary or secondary nodes are running), and may not initially start.</p> <p>Workaround: Stop the unresponsive secondary server. Restart the primary server, and then restart the secondary server.</p>

Issue #	Description
RTC-299	<p>Uninstallation leaves undeleted registry entry if upgrade of Unwired Platform 2.2.x to SAP Mobile Platform 2.3 required cluster name to be truncated.</p> <p>The Unwired Platform 2.2.x installation created a registry value for the name of the cluster, <code>clusterdb_<clustername></code>. SAP Mobile Platform 2.3 limits cluster names to no more than 16 characters in length. If the upgrade installer encountered a cluster name that was longer than 16 characters, it cloned the <code>clusterdb_<clustername></code> registry entry with the name <code>clusterdb_</code>, and did not delete the original <code>clusterdb_<clustername></code> registry entry. SAP Mobile Platform 2.3 does not delete that entry.</p> <p>Workaround: Manually delete the <code>clusterdb_<clustername></code> registry entry if you want to; however, leaving it in place will not cause any problems with future reinstallation of SAP Mobile Platform.</p>
RTC-267	<p>Upgrade process stops responding when calling <code>start-unwired-services.bat</code>.</p> <p>The upgrade process stops responding after upgrading the first server node if all nodes were not shut down before the upgrade.</p> <p>Workaround: Online upgrade is not supported. Stop all the SAP Mobile Platform services, including the data tier, before running the upgrade installer.</p>
RTC-34	<p>Warning messages when installing secondary SAP Mobile Server node.</p> <p>When installing a secondary SAP Mobile Server node before the primary server successfully installs, you see a warning similar to this in the server log:</p> <pre>2012-08-21 01:26:15.753 WARN MMS ScheduledTask:SynchronizeNode...</pre> <p>Workaround: Ignore this warning, or install the secondary SAP Mobile Server node after the primary server installation completes.</p>
CR-692901	<p>SAP® JCo 3 in Unwired WorkSpace running on Windows XP requires Microsoft Visual C++ 2005 Service Pack 1 Redistributable.</p> <p>Note: This is not a requirement for Windows 7, or 64-bit Windows Server 2008 system.</p> <p>Workaround: Obtain the Microsoft Visual C++ 2005 Service Pack 1 Redistributable from:</p> <p>http://www.microsoft.com/download/en/details.aspx?displaylang=en&id=14431.</p>

Issue #	Description
CR-665409	<p>The installation program cannot run in graphical mode.</p> <p>If the HKLM\SOFTWARE\Microsoft\Windows NT\CurrentVersion\AppCompatFlags registry key contains an entry that is the path of the installer binary (for example, C:\setup.exe), you see this error, and the installation fails:</p> <p>The installer is unable to run in graphical mode. Try running the installer with the -console or -silent flag.</p> <p>Workaround: Remove the installer binary path from the HKLM\SOFTWARE\Microsoft\Windows NT\CurrentVersion\AppCompatFlags registry key.</p>
CR-590885	<p>Uninstaller might not run on Windows Vista.</p> <p>This may be caused by the operating system changing the launch command for the SAP Mobile Platform uninstaller, preventing it from using its own JVM to start itself.</p> <p>Workaround: Launch the uninstaller:</p> <pre><jdk_installdir>\java -Dtemp.dir=%TEMP% -jar C:\Sybase\UnwiredPlatform\Uninstallers\UnwiredPlatform\uninstall.jar</pre> <p>When you uninstall or cancel out of uninstalling SAP Mobile Platform, the Program Compatibility Assistant shows:</p> <p>This program might not have uninstalled correctly.</p> <p>Select This program uninstalled correctly instead of Uninstall with recommended settings.</p>

Known Issues for Security

Learn about known issues and apply workarounds for SAP Mobile Platform security.

Issue #	Description
SMPONP-12442	<p>Changes to SQL Anywhere Server and Utility</p> <p>See <i>SQL Anywhere Servers and Utilities Use OpenSSL</i> on page 55.</p>
RTC-60	<p>SAP Mobile Server restart is needed after changing keystore.</p> <p>Workaround: If you change anything relating to keys or certificates in the key-store, you must always restart the server. Changes only take effect after a server restart.</p>

Issue #	Description
CR-708833	<p>External authentication token is not properly handled by iOS Hybrid Web Container (HWC).</p> <p>Workaround: For an external token to be passed to and used by iOS Hybrid Web Container for performing single sign-on (SSO), make the call to <code>setHttpHeaders</code> before starting the client engine by placing <code>[self setHttpHeaders]</code> in the first line in the <code>startEngine</code> function. See <i>Setting HTTP Headers</i> in <i>Developer Guide: Hybrid App Packages</i>.</p>

SQL Anywhere Servers and Utilities Use OpenSSL

SQL Anywhere Servers and Utilities Use Cryptographic Software Provided by OpenSSL, which introduce behavioral changes described here.

SQL Anywhere Server and Utility changes include:

1. Server identity uses AES encryption, previously it used 3DES encryption. Server certificates used by older servers (using FIPS) had private keys encrypted with 3DES which is no longer allowed. See *Converting certificates for use with FIPS* on page 55 for instructions on modifying existing certificates so they can be used with a new server.
2. Self-signed server certificates must now have the “Certificate Signing” attribute set.
3. TLS/SSL connections to a MobiLink server using client-side certificates now require the client-side certificate to have the “Digital Signature” attribute set, otherwise the connection fails.
4. Utility changes:
 - The **createcert** utility now encrypts the private key of the certificate it creates with AES rather than the less secure 3DES. Certificates using AES cannot be used by older SQL Anywhere software. If you need such compatibility, specify the new “-3des” switch to instruct createcert to use 3DES instead.
 - The **viewcert** utility now uses AES rather than 3DES to encrypt the private key when using -p to PEM -encode the output and -ip / -op to set the password. You can specify the new “-3des” switch to tell viewcert to use 3DES instead.

Converting certificates for use with FIPS

Certificates used by servers using FIPS are no longer accepted. This is because the older FIPS module only accepted certificates with private keys encrypted with 3DES. The OpenSSL FIPS module does not allow 3DES to be used, so the private keys must be encrypted with AES. It is possible to re-encrypt the private key, rather than generating new certificates, using the viewcert utility. Use this syntax: `viewcert -p -o <new file> -op <new password> -ip <old password> <old file>`

This creates a new certificate file with an AES-encrypted private key. The new and old passwords can be the same. The server must then use the new file instead of the old one. The certificate files used by clients do not need to change.

You can run the OpenSSL `viewcert` command against your certificate to determine if the “Key Usage” attributes are set appropriately. For example:

```
viewcert -ip sql
```

```
client_id.pem
```

```
SQL Anywhere X.509 Certificate Viewer Version 16.0.0.1642
```

```
X.509 Certificate
```

```
-----
```

```
Common Name: iAnywhere
```

```
Country Code: CA
```

```
State/Province: Ontario
```

```
Locality: Waterloo
```

```
Organization: SAP
```

```
Organizational Unit: Sybase
```

```
Issuer: iAnywhere
```

```
Serial Number: 1ff932e3bb534398810066d26678f80e
```

```
Issued: Oct 17, 2013 10:55:00
```

```
Expires: Oct 18, 2033 10:55:00
```

```
Signature Algorithm: RSA, SHA256
```

```
Key Type: RSA
```

```
Key Size: 1024 bits
```

```
Basic Constraints: Is not a certificate authority
```

```
Key Usage: Digital Signature, Key Encipherment, Data Encipherment,
```

```
Key Agreement, Certificate Signing
```

```
Private Key
```

```
-----
```

```
Key Type: RSA
```

```
Key Size: 1024 bits
```

Known Issues for SAP Mobile Server

Learn about known issues and apply workarounds for SAP Mobile Server.

Issue #	Description
SMPONP-15180	<p>Information remains in the clusterdb after uninstalling a cluster node.</p> <p>Server node still appears in SAP Control Center after uninstallation of the node.</p> <p>Workaround: This issue does not affect runtime behavior. You can remove the server node completely by manually executing this SQL script on the clusterdb database:</p> <pre> DELETE FROM PACKAGE_SYNC_DATA WHERE NODENAME IN (SELECT mp.VALUE1 FROM MEMBER_PROP AS mp, CLUSTER_MEMBER AS cm WHERE mp.NAME='sup.appservername' AND mp.MEMBERID = cm.MEMBERID AND cm.NAME LIKE '####toDelete'); DELETE FROM SYNC_VERSION WHERE NODE_NAME IN (SELECT mp.VALUE1 FROM MEMBER_PROP AS mp, CLUSTER_MEMBER AS cm WHERE mp.NAME='sup.appservername' AND mp.MEMBERID = cm.MEMBERID AND cm.NAME LIKE '####toDelete'); DELETE FROM installation_info WHERE host_name IN (SELECT mp.VALUE1 FROM MEMBER_PROP AS mp, CLUSTER_MEMBER AS cm WHERE mp.NAME='sup.host' AND mp.MEMBERID = cm.MEMBERID AND cm.NAME LIKE '####toDelete'); DELETE FROM installation_history WHERE host_name IN (SELECT mp.VALUE1 FROM MEMBER_PROP AS mp, CLUSTER_MEMBER AS cm WHERE mp.NAME='sup.host' AND mp.MEMBERID = cm.MEMBERID AND cm.NAME LIKE '####toDelete'); DELETE FROM MEMBER_PROP FROM MEMBER_PROP as mp, CLUSTER_MEMBER AS cm WHERE mp.MEMBERID = cm.MEMBERID AND cm.NAME LIKE '####toDelete'; UPDATE CLUSTER_INSTALLATION SET HOSTNAME = HOSTNAME '####toDelete' WHERE INSTALLID IN (SELECT cm.INSTALLID FROM CLUSTER_MEMBER AS cm WHERE cm.NAME LIKE '####toDelete') DELETE FROM CLUSTER_MEMBER WHERE NAME LIKE '####toDelete' DELETE FROM CLUSTER_INSTALLATION WHERE HOSTNAME LIKE '####toDelete'; </pre>

Issue #	Description
SMPONP-15176	<p>In a shared host Microsoft cluster environment, Hazelcast selects the wrong IP address when starting SAP Mobile Server, which prevents the secondary server node from starting.</p> <p>In these cases, a server log message similar to this appears on the primary server node:</p> <pre>2014-03-10 22:30:09.217 INFO Other main [com.hazelcast.impl.AddressPicker] [] [] Interfaces is disabled, trying to pick one address from TCP-IP config addresses: [] 2014-03-10 22:30:09.217 WARN Other main [com.hazelcast.impl.AddressPicker] [] [] Could not find a matching address to start with! Picking one of non-loopback addresses. 2014-03-10 22:30:09.504 INFO Other main [com.hazelcast.impl.AddressPicker] [] [] Picked Address [10.58.120.84] :5701 using socket ServerSocket [addr=/0:0:0:0:0:0:0:0,localport=5701] , bind any local is true 2014-03-10 22:30:10.156 INFO Other main [com.hazelcast.system] [] [] [10.58.120.84] :5701 [2.3.4 SHC default] Hazelcast Community Edition 2.1.3 (20120723) starting at Address [10.58.120.84] :5701</pre> <p>Workaround: Either:</p> <ol style="list-style-type: none"> <ol style="list-style-type: none"> Start the SAP Mobile Server node which is sharing the host with the data-tier node. Start the other SAP Mobile Server node to resolve the IP address for the first node. Restart the first SAP Mobile Server node in order to make sure it binds to the correct IP address. Or: Run this SQL statement for each SAP Mobile Server node: <pre>update cache_addr_mapping set ip_addr = 'xxx.xxx.xxx.xxx' where host_name = 'SERVERNAME'</pre> <p>where <i>SERVERNAME</i> is the server's host name without the domain suffix, and <i>xxx.xxx.xxx.xxx</i> is the IP address.</p>
SMPONP-12328	<p>jetty-web.xml was removed from . . \DCN\WEB-INF folder</p> <p>Problem: DCN POST results in error message that the form is too large.</p> <p>Workaround: Set the maxFormContentSize property to 100 MB:</p> <ol style="list-style-type: none"> In SAP Control Center, select Configuration. Set the value of Max form content size(byte) to 10000000. Restart the server.

Issue #	Description
SMPONP-11956	<p>Select socket timeout property</p> <p>In the connection pool, select a socket timeout property from the drop-down list:</p> <ul style="list-style-type: none"> • 0 overrides the socket time out property and ensures that request response will go through • higher than the gateway response time ensures that request response goes through successfully • lower than the gateway response time - ensures that the request fails and throws - 500 (Internal server error)
SMPONP-7973	<p>Disregard "Error applying pending settings..." in logs under ..\APNSProvider and ..\BlackBerryNotifier</p> <p>"Error applying pending settings, using old settings instead" messages can be found in ..\Servers\UnwiredServer\logs\APNSProvider and ..\Servers\UnwiredServer\logs\BlackBerryNotifier. Ignore these messages.</p>
CSN-2990597 2013	<p>Certificate onboarding fails after upgrade</p> <p>After upgrading to SAP Mobile Platform version 2.3 SP03, certificate onboarding will fail if certain obsolete properties remain configured.</p> <p>Workaround: Modify the security configuration in SAP Control Center by removing the following properties:</p> <ul style="list-style-type: none"> • Trusted certificate store type • Trusted certificate store password • Trusted certificate store provider • Validate certification path • Trusted certificate store

Issue #	Description
SMPONP-10928	<p>Temporary network issues affecting the cluster</p> <p>During some operations, for example, deploying packages after switching a data tier in the Microsoft cluster, or failing to connect to the data tier in a simple cluster, a temporary network issue causes the following warning message to be logged in the server log:</p> <pre> 2013-09-04 02:16:05.362 WARN MMS Thread-256 [com.sybase.sup.server.deploy.SupDeployer] [] [] System.Web.Services.Protocols.SoapException: Error sending request to server at Admin.AddTemplate(String strTemplateName, String strTemplateDescription, PropertyItem[] settings) java.lang.RuntimeException: System.Web.Services.Protocols.SoapException: Error sending request to server at Admin.AddTemplate(String strTemplateName, String strTemplateDescription, PropertyItem[] settings) at com.sybase.sup.admin.util.WebServiceUtil.createTemplate(WebServiceUtil.java:219) at com.sybase.sup.admin.util.WebServiceUtil.createTemplate(WebServiceUtil.java:209) at com.sybase.sup.server.deploy.SupDeployer.createTemplate(SupDeployer.java:797) at com.sybase.sup.server.deploy.SupDeployer.saveApplicationInfo(SupDeployer.java:776) at com.sybase.sup.server.deploy.SupDeployer.doDeploy(SupDeployer.java:734) at com.sybase.sup.server.deploy.SupDeployer.deploy(SupDeployer.java:306) at com.sybase.sup.admin.server.DomainAdminImpl.deployWithArgs(DomainAdminImpl.java:365) at com.sybase.sup.admin.server.DOECDomainAdminImpl_DJC.\$invoke_0(DOECDomainAdminImpl_DJC.java:384) at com.sybase.sup.admin.server.DOECDomainAdminImpl_DJC.\$invoke(DOECDomainAdminImpl_DJC.java:147) at com.sybase.djc.rmi.iiop.server.MessageHandler.processRequest(MessageHandler.java:794) at com.sybase.djc.rmi.iiop.server.MessageHandler.run(MessageHandler.java:306) at java.util.concurrent.ThreadPoolExecutor.runWorker(ThreadPoolExecutor.java:1145) at java.util.concurrent.ThreadPoolExecutor\$Worker.run(ThreadPoolExecutor.java:615) at java.lang.Thread.run(Thread.java:789) </pre> <p>Workaround: Redeploy the package after the cluster returns to normal.</p>
SMPONP-9999	<p>When one SAP Mobile Server node in a cluster restarts, other nodes may throw <code>com.hazelcast.core.MemberLeftException</code>.</p> <p>Workaround: The cache's status recovers after a brief period of time or when the server restarts completely. The exception is temporary and can be ignored.</p>

Issue #	Description
SMPONP-9965	<p>Key store and Keypair passwords must match</p> <p>:If the key store and keypair passwords do not match, you are unable to save the certificate alias, and receive the following error message:</p> <p>Save failed. Cannot recover key.</p> <p>Workaround: Configure the key store and keypair passwords as follows:</p> <ol style="list-style-type: none"> 1. While configuring the SAP Mobile Server for mutual SSL, generate the keypair with the same password as the keystore password. For example, if the keystore.jks has password "changeit", the corresponding keypair generated must also have the password "changeit". 2. Save the keystore file. 3. Check for the correctness using the following from the command prompt: C:\>keytool -list -alias alias_name -keystore keystore.jks -storepass changeit 4. Restart the services. 5. Set the alias value in the SAP Control Center SSL configuration tab. The save is successful. 6. Restart the server to apply the changes.
SMPONP-8310	<p>SAP Mobile Server experiences significant performance degradation when performing DCN load operations with large DCN request messages when Wily Introscope agents are enabled.</p> <p>Workaround: If not required, remove the Introscope agents from SAP Mobile Server using this command: C:\SAP\MobilePlatform\Servers\UnwiredServer\bin\configure-introscope-agents.bat -remove</p>
SMPONP-7496	<p>Error launching Sybase Central (scjview.exe)</p> <p>In SAP Mobile Platform version 2.3 SP03, when you double click Sybase Central (scjview.exe) in the SQLAnywhere16/bin32 directory for database management, an internal error appears.</p> <p>Workaround: In the pop up window, click Resume to launch Sybase Central.</p>

Issue #	Description
SMPONP-1781	<p>Server-name fails to start due to an expired certificate</p> <p>The SAP Mobile Server cannot be started (the server shows started for a short time then shows stopped), and you receive the error "Stream Error: Internal error: ssl_AddTrustedCerts returned 4157" in the server log. This error occurs because a certificate expired in the <code>client_trusted_cert.crt</code> file.</p> <p>Workaround: To resolve the issue by removing the expired certificate:</p> <ol style="list-style-type: none"> 1. Backup the <code>client_trusted_cert.crt</code> file on the server certificate folder. 2. Keep one valid certificate in <code>client_trusted_cert.crt</code>, remove the other certificates and save the file. 3. Restart the server. The server starts up successfully. 4. Log in to SAP Control Center, go to the Configuration > General > SSL Configuration tab, and click Key Store configuration to open the Key Store Properties dialog, 5. Check all the certificates in key store. Find the expired certificate marked in red, and remove it from the key store. The <code>client_trusted_cert.crt</code> will be automatically generated again. 6. Restart the server. The server start up successfully because the expired certificate has been removed from <code>client_trusted_cert.crt</code>.
RTC-302	<p>XML recordings are saved to an incorrect directory.</p> <p>After enabling XML recording in the registry, logs will show that XML recordings are successfully saved to <code>C:\UnwiredServer\logs</code>, which is the incorrect SAP Mobile Platform logging directory.</p> <p>Workaround: Manually add a String Value to the key <code>HKEY_LOCAL_MACHINE\SOFTWARE\Sybase\Sybase Messaging Server\Server</code> (<code>HKEY_LOCAL_MACHINE\SOFTWARE\Wow6432Node\Sybase\Sybase Messaging Server\Server on 64 bit</code>) with a path relative to the <code>MessagingServer</code> directory (that is, <code>..\UnwiredServer\logs</code>).</p>
RTC-268	<p>Process of stopping SAP Mobile Server service hangs.</p> <p>When stopping the Windows service for SAP Mobile Server, very infrequently the process hangs. This problem is independent of the means used to stop the service.</p> <p>Workaround: See <i>Process of Stopping SAP Mobile Server Service Hangs</i>.</p>

Issue #	Description
RTC-238	<p>Update deployment allows definition of a new MBO attribute default, but the new default value does not take effect.</p> <p>While the MBO developer can modify the MBO attribute default value for a deployed package, and redeploy the package to SAP Mobile Server in Update mode without an error or warning, the new default value does not take effect.</p> <p>Workaround: Use Replace mode to update the MBO default setting.</p>
RTC-42	<p>Business transaction XML (BTX) uploads when end-to-end tracing is not enabled for an application connection.</p> <p>You can still upload BTX to the configured Solution Manager server, even if you have not enabled end-to-end tracing for an application connection.</p> <p>Workaround: None.</p>
RTC-38	<p>Server logs Chinese environments result in garbled characters under certain conditions.</p> <p>Due to an issue with SySAM licensing 64-bit operating systems running in a zh_CN locale result in characters appearing incorrectly.</p> <p>Workaround: None.</p>
N/A	<p>Error: 584 Message: Server public key verification failed when running the diagtool.exe tool.</p> <p>Workaround: Either:</p> <ul style="list-style-type: none"> • Run the diagtool.exe tool from another host, or, • Edit the registry on the machine where the diagtool.exe tool is being run: <ul style="list-style-type: none"> • Remove the HKCU\Software\Sybase\Messaging Client registry key. • Remove the HKCU\Software\Sybase\Messaging-ClientLib registry key. <hr/> <p>Note: Use caution when editing the registry. Ensure that the key entries removed do not contain any currently used SAP Mobile Platform applications (sub entries).</p>
CR-709892	<p>SAP Mobile Server records deployment errors in the domain log rather than in the SAP Mobile Server logs.</p> <p>Workaround: None. Look for deployment errors in the domain log.</p>

Issue #	Description
CR-708431	<p>Data on the EIS, cache, and device is not in sync.</p> <p>If a Create operation succeeds at the enterprise information system (EIS), but its corresponding Entity Read operation fails, the EIS is updated but the cache database (CDB) is not. Error information may be reported in the SAP Mobile Server log, but the error is not propagated to the device client. LogRecord shows 0 (zero), but findAll does not show the new record on the device.</p> <p>Workaround: None. The change appears in the CDB and the device when the CDB is refreshed (for example, when the cache interval expires).</p>
CR-703515	<p>LDAP role/authentication search base cannot support special characters.</p> <p>The following characters have special meaning when they appear in a name in LDAP: , (comma), = (equal sign), + (plus sign), < (less than), > (greater than), # (number sign), ; (semicolon), \ (backslash), and " (quotation mark).</p> <p>LDAP providers do not currently handle these special characters in any names or DN's, including user name, DefaultSearchBase, AuthenticationSearchBase, RoleSearchBase, AuthenticationFilter, and RoleFilter.</p> <p>Workaround: None.</p>
CR-701975	<p>When deploying a package from Unwired Workspace or SAP Control Center using Update mode, the package's "onDemand" coherence window is not updated on SAP Mobile Server.</p> <p>Workaround: After deployment, adjust the "onDemand" coherence window from SAP Control Center.</p>
CR-699590	<p>Large messages are processed incorrectly on 32-bit runtime installations.</p> <p>A 32-bit SAP Mobile Server is not supported when you are developing messaging applications that process large messages. 32-bit servers run into memory issues and can potentially further result in incorrect data synchronizing with the SAP Mobile Server cache.</p> <p>Workaround: Install SAP Mobile Platform runtime components on 64-bit hosts.</p>

Issue #	Description
CR-699343	<p>For native Object API applications, the upgrade process silently deletes composite orphans from the server cache.</p> <p>SAP Mobile Platform no longer allows composite orphans, that is MBO child entities within a composite relationship that have no parent entity. Depending on the system configuration, the upgrade may physically delete the orphans, or may only logically delete them, then physically delete them during a subsequent cache purge process. Either way, applications that use MBOs with composite orphans may not behave as expected after migration.</p> <p>Workaround: Before upgrading, eliminate composite orphans from native Object API applications:</p> <ul style="list-style-type: none"> • Look for existing MBOs that generate composite orphans. Examine each MBO in Unwired WorkSpace, looking for any instance in which the application loads child entities before the related parent entity. • For any MBOs you find that generate composite orphans, change the data model in the MBO so that the application always loads parent entities before the related child entities. See the "Composite relationship behavior" row in the <i>Relationship Guidelines and Restrictions</i> topic, in the <i>Sybase Unwired WorkSpace - Mobile Business Object Development</i> guide. • Test any changes you make to ensure that the application still behaves as expected. • After you are satisfied that you have eliminated composite orphans from your MBOs, proceed with the upgrade. <p>Additional Information on Composite Orphans</p> <p>An example of a scenario in which parentless child entities can occur is a two MBO parent-child model integrated with JDBC for sales orders and line items. If the data model specifies that line items are inserted first, the application attempts to load child line items for a sales order that does not yet exist. Those line items disappear from the cache before the application can load the parent sales order.</p> <p>To be sure that composite orphans do not cause problems in your migrated applications:</p> <ul style="list-style-type: none"> • After migration, if you have mobile application projects that contain composite relationships and the child MBO load operation has no parameter dependencies on its parent, redeploy the package from Unwired WorkSpace using Update mode to generate the correct loadGroups for the deployed package. • Child load operations that do not depend upon parameters from the parent do not always generate orphans. <p>Consider the case where the user wants to load all sales orders and line items created in the New York office. New York may be a load parameter for both parent and child that is bound to a personalization key and results in no orphans even though the child does not get any load parameters from the parent.</p>

Issue #	Description
CR-695671	<p>The <code>mlsrv_err.log</code> reports error: <code>java.lang.OutOfMemoryError</code>.</p> <p>When performing a listview object query with very large data sets, the client returns an error code 571 or 1053, and the server becomes temporarily unavailable, or tries to restart.</p> <p>Workaround: Modify the maximum Java heap size to handle very large amounts of data in an object query. See <i>Configuring SAP Mobile Server Performance Properties</i> in <i>System Administration</i>.</p>
CRs 693116 and 692218	<p>Devices on 3G/4G network cannot connect to SAP Mobile Server.</p> <p>A connectivity issue may occur between the device and SAP Mobile Server. The current client libraries use a protocol that support only HTTP chunked transfer-encoding. 3G/4G traffic might, in some cases, be subject to content filtering and convert the messages from chunked transfer-encoding to fixed content-length if communication is via standard HTTP ports, which most commonly are 80 and 8080. Since the client application can support only chunked transfer-encoding, the communication cannot be established. In effect, a response cannot be returned to the server indicating that the device is online.</p> <hr/> <p>Note: For devices on Wi Fi networks, the connection between a device and SAP Mobile Server establishes without error.</p> <hr/> <p>Workaround: Use a nonstandard HTTP port (any port other than 80 or 8080) or an HTTPS port, that is, 443 for SAP Mobile Server client communication from devices to the Relay Server or external load balancer, whichever one is used, in the DMZ.</p>
CR-692374	<p>Enabling compression incurs additional processing on the device and the server side to optimize the amount of data to be transferred over the network.</p> <p>Workaround: Carefully evaluate whether the compression trade-off is appropriate in the deployment environment, and carefully size the server capacity to support it. If appropriate in a particular environment, follow the <i>SAP Mobile Platform Developer Guides</i> to enable compression.</p>
CR-691517	<p>Adding new operations onto a mobile business object in a deployed package using the Update deployment method may render client applications based on the previous package model version nonfunctional.</p> <p>Workaround: None.</p>
CR-686043	<p>In a disabled domain, messaging clients continue to receive messages from server.</p> <p>Workaround: To disable any outbound activity to a client, lock the application connection associated with that client.</p>

Issue #	Description
CR-576726	<p>The full range of valid values is not supported if an attribute uses the default datatype (int) for a SQL Anywhere® database column of type unsigned int.</p> <p>Workaround: To support the full range of valid values for an unsigned int attribute in the EIS, set the datatype for the corresponding MBO attribute as long.</p>
NA	<p>When stopping the Windows service for SAP Mobile Server, very infrequently the process stops responding. This problem is independent of the means used to stop the service.</p> <p>When this happens, the process tree for the service for the SAP Mobile Server service is no longer intact, so you cannot use the Task Manager End Process Tree option to stop the service.</p> <p>Workaround:</p> <ol style="list-style-type: none"> 1. Open Windows Task Manager on the system where you want to stop the SAP Mobile Server service. 2. Activate the Process tab and click the Image Name column heading to sort the names in alpha order. 3. For each of the following processes that are present in the list, right-click the process and select End Process. <ul style="list-style-type: none"> • AdminWebservices.exe • AMPService.exe • Dbsrv16.exe • Dbsrv11.exe • Java.exe • JmsBridge.exe • LBManager.exe • mlsrv16.exe • MlsrvWrapper.exe • OBMO.exe • OBServiceManager.exe • Rsoe.exe • Sccservice.exe • wmioprse.exe 4. Go to the Windows Services panel and verify that the SAP Mobile Server service is stopped.

Known Issues for Agentry Server

Learn about known issues and apply workarounds for Agentry Server.

Issue #	Description
N/A	<p>Agentry Server 6.1 should report versioning information to a central landscape management tool.</p> <p>Workaround: Agentry Server stores the version information in a system file. A user can determine the Agentry Server version by navigating in File Explorer to the Agentry Server executable and right-clicking the file properties to determine the versioning information.</p>
RTC-440	<p>In an SAP Control Center cluster, if a server node is restarted when an Agentry application is stopped (not disabled), then when SAP Mobile Platform restarts, the node and Agentry Server get into differing states.</p> <p>If you have an application stopped, not disabled, and a server node comes down, then when the node restarts, the Agentry server on that node starts and causes the nodes to be in different states. This causes all the “Start/Stop/Restart” buttons to become disabled. You must either restart the Agentry node or delete the application and start over.</p> <p>Workaround: None.</p>

Known Issues for SAP Control Center

Learn about known issues and apply workarounds for SAP Control Center.

Issue #	Description
SMPONP-15058	<p>Product information from the Installed History tab of SAP Control Center does not display details of older SPs or patches.</p> <p>Workaround: Check details in the product_patch_info, product_patch_components, and product_component_files tables in the clusterdb database.</p>

Issue #	Description
SMPONP-14823	<p>Selected properties do not show correctly when switching between tabs in SAP Control Center.</p> <p>For example:</p> <ol style="list-style-type: none"> 1. Log in to SAP Control Center and go to Applications. 2. Click a specified Application > Application Connections . 3. Select hidden properties such as Client version 4. The page displays the properties, but if you go back to Application > Application Connections, the hidden properties are selected but do not display. <p>Workaround: Select the properties you want to show by selecting it on the current page's drop-down list to invoke the add columns event.</p>
SMPONP-14818	<p>Newly created Web Container properties cannot be edited and saved by clicking the Properties button if not first saved.</p> <p>If you:</p> <ol style="list-style-type: none"> 1. Create a new Web Container from SAP Control Center 2. Make changes, for example, define a port number 3. Click OK in the pop up dialog, then select the newly created port and click Properties 4. Update the port number, click OK, save the changes, and restart the server <p>The port number is not updated.</p> <p>Workaround: After creating a new Web Container record, click Save before editing the properties.</p>
SMPONP-14802	<p>Changing OCSF (Online Certificate Status Protocol) properties from a valid value (not empty) to NULL (empty string), requires server restart.</p> <p>If you change an OCSF property to NULL from SAP Control Center, then click Save, your changes do not take effect.</p> <p>Workaround: Restart SAP Mobile Server for the OCSF changes to take effect.</p>
SMPONP-14405	<p>The warning message "the service did not respond to the start or control request in a timely fashion" displays when stopping SAP Mobile Server</p> <p>Occasionally when stopping the SAP Mobile Server service from the Windows service control panel, you may encounter the warning message described above.</p> <p>Workaround: You can safely ignore the warning message, the process eventually stops as expected.</p>

Issue #	Description
SMPONP-9158	<p>Unable to restart a remote SAP Mobile Server.</p> <p>If a firewall blocks all UDP and TCP packets, attempts to use a local SAP Control Center to restart a remote SAP Mobile Server fail.</p> <p>Workaround: Use the local SAP Control Center to restart the local SAP Mobile Server.</p>
RTC-373	<p>SAP Control Center shows "Unable to retrieve the child managed objects" error dialog when removing an MBO package.</p> <p>Workaround: This problem is most likely caused when the SAP Control Center host machine network address has changed while the user is performing an operation in SAP Control Center. Close your browser session and relaunch the SAP Control Center URL.</p>
RTC-309	<p>If the user installs SAP Mobile Platform in the root directory of the file system (such as C:\), then the SLD data supplier fails to work.</p> <p>Workaround: Avoid installing SAP Mobile Platform in the root directory of the file system.</p>
RTC-221	<p>Redeploying a package to SAP Mobile Server after changing a Cache Group policy from "Scheduled" to "On Demand" may result in SAP Control Center displaying an invalid cache interval.</p> <p>Workaround: Update the cache interval in SAP Control Center.</p>
CR-707565	<p>Domain log purging can take a significant amount of time if too much data accumulates.</p> <p>Workaround: Purge the domain log at regular intervals.</p>
CR-705003	<p>SAP Control Center does not ask user to delete packages and connections before deleting the domain.</p> <p>Workaround: Before you delete a domain, verify package and connection deletion is not an issue.</p>
CR-704917	<p>If an administrator takes action from SAP Control Center while the primary server is being shut down, you may see an internal or unexpected error if the server has not completely shut down.</p> <p>Workaround: Before taking any action in SAP Control Center, ensure that the primary server shutdown is complete and another server has taken over as the new primary.</p>
CR-704913	<p>When an iOS device goes offline, it continues to show as being online for about 8 minutes in SAP Control Center.</p> <p>Workaround: None.</p>

Issue #	Description
CR-703367	<p>Domain log messages in Data Sync and Operation Replay subsystems are not logged to the default domain.</p> <p>Workaround:</p> <ul style="list-style-type: none"> • Create a domain log profile for the 'default' server connection (JDBC type) to enable logging of Data Sync and Operation Replay messages. • If you have a similar configuration, make changes as appropriate. Contact Technical Support for guidance.
CR-703321	<p>Exporting a domain log after upgrading generates a Domain log export failed error message.</p> <p>Workaround: Clear the cache for the browser you are using to access SAP Control Center.</p>
CR-696373	<p>When retrieving a domain log for large data, you receive an unknown error in SAP Control Center.</p> <p>Workaround: Check whether the SAP Mobile Server or SAP Control Center agent.log reports an out of memory error. If so, increase the JVM heap size appropriately for SAP Mobile Server from the SAP Control Center Configuration tab.</p> <p>If this does not resolve the issue, try decreasing the time range set in the domain log in SAP Control Center.</p>
CR-695792	<p>Suspending a large volume (100 or more) of DOE-C package subscriptions may cause SAP Mobile Server to stop responding.</p> <p>Workaround: Suspend subscriptions in batches of no more than 50.</p>
CR-691963	<p>MBO package deployment in Update mode after adding a new load argument without default value succeeds even though deployment should fail.</p> <p>Workaround: None. To avoid deploying client-incompatible changes, SAP recommends that you first use Verify mode deployment; if verify succeeds, proceed to Update mode deployment.</p>

Issue #	Description
CR-690482	<p>Using Firefox, the SAP Control Center main page shows Invalid Login and the agent.log shows Received fatal alert: bad_certificate error.</p> <p>Workaround: The Firefox browser appears to be using an incorrect server certificate. Clean up any such previously existing certificates:</p> <ol style="list-style-type: none"> 1. in SAP Control Center, select Tools > Options > Advanced > View Certificates. 2. Click the Servers tab, then identify existing certificates issued to the same host to which you are connecting. 3. Click Delete to remove all such certificates. Alternatively, use Internet Explorer.
CR-683775	<p>In some instances, when using the Windows Services tool or the Stop SAP Mobile Platform Services shortcut to stop the SAP Control Center3.2 service, SAP Control Center displays Stopping in the Windows Control Panel yet fails to stop.</p> <p>Workaround: To stop the SAP Control Center service:</p> <ol style="list-style-type: none"> 1. Launch Windows Task Manager. 2. Locate the <code>sccservice.exe</code> process, right-click and select End Process Tree. This option also kills the SAP Control Center database repository server process <code>dbsrv11.exe</code>.

Known Issues for SAP® Data Orchestration Engine Connector

Learn about known issues and apply workarounds for SAP® Data Orchestration Engine Connector (DOE-C).

Issue #	Description
SMPONP-11521	<p>Issue with security configuration assignment in silent mode in the DOE-C command line utility.</p> <p>In the DOE-C command line utility, when you try to assign a non-existing security configuration to a package in silent mode, the package's security configuration is set to empty.</p> <p>Workaround: Do not try to assign a non-existing security configuration to a package in silent mode.</p>

Issue #	Description
SMPONP-2901	<p>ESDMA package deployment fails if the DOECNoAuth security configuration does not exist.</p> <p>When deploying an ESDMA package using the DOE-C CLU or the DOE-C Admin API, the deployment fails if there is no DOECNoAuth security configuration. After a first failed deployment, an attempt to do a second deployment is successful because the DOECNoAuth security configuration has been created.</p> <p>Workaround: Ensure the DOECNoAuth security configuration exists.</p>
RTC-262	<p>Error occurred during command execution: 'deploy' . message appears when deploying DOE-C package.</p> <p>Workaround: Examine the SAP Mobile Server log file. See <i>Server Log</i> in <i>System Administration</i>.</p> <p>If you see NoSuchElementException in the log file at about the time the error message appeared, ignore the error and redeploy.</p>
RTC-207	<p>For a DOE-C package, if a device with an expired X.509 certificate initiates unsubscribe, it indicates that the DOE subscription is not cleaned up.</p> <p>Workaround: The DOE administrator must manually clear all such disconnected DOE subscriptions.</p>
RTC-39	<p>Package Not found error occurs randomly when DOE-C package is deployed on a cluster.</p> <p>Workaround: Redeploy the package.</p>
RTC-28	<p>Long response time to show DOE-C subscription with packet-dropped state.</p> <p>When a DOE-C subscription encounters a packet-dropped state, it takes more than 10 minutes to show the updated subscription information on the Subscription tab in SAP Control Center.</p> <p>Workaround: None.</p>
CR-709691	<p>SAP Mobile Server fails with OutOfMemory error during subscription SUSPEND/RESUME operations.</p> <p>Workaround: In SAP Control Center, select Configuration > General > performance configuration and set the default value for Maximum number of in memory messages to 100.</p>

Issue #	Description
CR-708754	<p>When the load balancer is shut down due to an HTTP 404 error, DOE-C package subscriptions may be automatically removed.</p> <p>Workaround:</p> <ol style="list-style-type: none"> 1. Implement SAP note number 1722501 to prevent DOE from automatically removing subscribed users. 2. Create a scheduled job to execute the report, SDOE_RESTART_OUTBOUND_QUEUES to restart the queues in regular intervals in the DOE system.
CR-706532	<p>Suspend/Resume operations on DOE-C subscriptions may result in HTTP 502 - Bad gateway error in DOE when load balancer is between SAP Mobile Server and DOE.</p> <p>Workaround: Resume only a few subscriptions simultaneously. For example, you can suspend 100 users in a single operation, then repeat that procedure 10 times.</p>
CR-706111	<p>DOE-C error: HTTP 400, Unable To Parse Request while resuming more than 100 users at a time.</p> <p>Workaround: Resume only a few subscriptions simultaneously. For example, you can suspend 100 users in a single operation, then repeat that procedure 10 times.</p>
CR-705888	<p>Domain deletion may cause HTTP 500 error in DOE-C device queue.</p> <p>When DOE sends data to a subscription for a device for which the domain has already been deleted from SAP Mobile Platform, then SAP Mobile Platform should send a recoverable HTTP 404 error, indicating that either the subscription or the domain is not found. Instead the DOE device queue shows an unrecoverable internal server error (HTTP 500) and the SAP Mobile Server log file has a <code>java.lang.IllegalStateException: domain already cleared</code> error.</p> <p>Workaround: Remove the subscription in DOE.</p>
CR-703909	<p>When DOE-C sets domain log context properties, it leaves the "domain name" field blank in the server log entry.</p> <p>Workaround: The domain name is set correctly in the DomainLog table.</p>
CR-700957	<p>If the DOE server is down, the device receives a long HTML exception.</p> <p>Workaround: None.</p>

Known Issues for Relay Server and Load Balancer

Learn about known issues and apply workarounds for Relay Server and Load Balancer.

Issue #	Description
SMPONP-15348	<p>A RSOE service using HTTPS cannot start because duplicate certificates are imported into the keystore.</p> <p>Importing duplicate certificates into the keystore prevents the RSOE service from starting.</p> <p>Workaround: Delete the duplicate certificate from the keystore (only leave one item), then restart the RSOE service.</p>
SMPONP-15011	<p>SAP Mobile Platform version 2.3 SP04 does not include the <code>quicksetup_apache</code> folder as did previous releases.</p> <p>Workaround: For Relay Server installation and configuration instructions on Apache, see <i>Landscape Design and Integration > Stage 3: Implement > Adding Relay Servers or Reverse Proxies > Installing Relay Server for Production Environments > Installing a Relay Server</i>, and either:</p> <ul style="list-style-type: none"> • <i>Installing Relay Server on Apache RedHat Enterprise</i> or, • <i>Installing Relay Server on Apache SUSE Enterprise</i>
SMPONP-14716	<p>Apache Load balancer is not retaining original request URL from the OData client.</p> <p>The Apache Load Balancer modifies the URL to whichever node to which it is forwarding, if <code>ProxyPreserveHost off</code>, which is the default.</p> <p>Workaround: If you use Apache as a Reverse Proxy or Load Balancer, set <code>ProxyPreserveHost on</code> so the ODP component inside SAP Mobile Server can retrieve the original request URL and add a cookie for it. See <i>ProxyPreserveHost Documentation</i></p>

Issue #	Description
RTC-340	<p>Requests fail with error 400 bad request with session error reported by RSOE</p> <p>This error typically happens after Relay Server has been restarted. Relay server maintains client socket and back-end server socket affinity using a section named <code>ias-rs-sessionid</code>, which is provided by the client application. With this mechanism, a stateful request can be transferred to the original back-end server, even from a different relay server in the relay server farm. After restarting the relay server, the socket and session affinity that originated from this relay server are both cleared, and the back-end server socket connection is dropped. The Outbound Enabler responds with a 400 error when it receives a request that is still using the previous <code>ias-rs-sessionid</code> value. Moreover, for a stateless request that does not provide the <code>ias-rs-sessionid</code>, relay server transfers the request to any back-end server in the targeted farm according to the load balancing algorithm.</p> <p>Workaround:</p> <ol style="list-style-type: none"> 1. In the relay server configuration file, create a property named <code>renew_overlapped_cookie</code> in the <code>backend_farm</code> configuration section. 2. Set the <code>renew_overlapped_cookie</code> default value to yes. In the future, Outbound Enabler will create new connections instead of responding with a 400 error.
RTC-46	<p>When an HTTP client connects through Relay Server to SAP Mobile Platform to get a proxy connection, the URL rewrite in the response is missing the Relay Server prefix information.</p> <p>Workaround: None.</p>

Documentation Issues and Updates for SAP Mobile Platform Runtime

Read about updates, corrections, and clarifications to the documentation released with SAP Mobile Platform Runtime.

Issue #	Description
SMPONP-16215	<p>The SAP Control Center online documentation provided with the product and the Web documentation on SAP Help Portal may be different starting with SAP Mobile Platform 2.3 SP04 and earlier. The SAP Control Center online help may contain information regarding the Resumable Synchronization feature, which is not available in SAP Mobile Platform.</p> <p>For SAP Mobile Platform 2.3 SP04 PL01, the SAP Control Center Web documentation version contains the latest information.</p>
SMPONP-16206	SAP Mobile Server fails to start if you remove the JVM option <code>EnableDebuggingOnDemand</code> from the SAP Control Center JVM Properties dialog.
SMPONP-16204	<p>A warning message does not display to prevent you from running the SAP Mobile Platform Runtime 2.3 SP04 PL01 32-bit installer on a 64-bit system.</p> <p>SAP Mobile Platform does not support running the 32-bit installer on a 64-bit system.</p>
SMPONP-11422	<p>SQL Anywhere® version 16 is included as part of SAP Mobile Platform versions 2.3 SP03 and later.</p> <p>Previous releases of SAP Mobile Platform included SQL Anywhere version 12. The current documentation still contains references to SQLAnywhere12 as a product, directory path, and documentation location. These references should be SQL Anywhere 16 (product), SQLAnywhere16 (path), and http://dcx.sybase.com/index.html#sa160/en/sqlanywhere_en16/help_top_index.htm (documentation location).</p>
SMPONP-3399	<p>Improvement to sample test program for MBS performance testing with LoadRunner.</p> <p>In <i>System Administration</i>, the <i>Enabling MBS Performance Testing with LoadRunner</i> topic provides sample test program to show how to perform load testing of MBS in SAP Mobile Platform with LoadRunner. The documentation includes the <code>BeginOnlineLogin</code> method in <code>Action.cs</code>.</p> <p>An update to this content is that it is better to call <code>BeginOnlineLogin</code> in <code>vuser_init.cs</code>, rather than in <code>Action.cs</code>. A client application should not need to login more than once, even if the Action is to be repeated multiple times during a benchmark run.</p>

Issue #	Description
N/A	<p>Requirements for a computer name, used as default server or cluster name when installing SAP Mobile Server, are not listed.</p> <p>The <i>Installation Guide for Runtime</i>, <i>Selecting Installation Options</i> sections of the tasks that install a new instance of SAP Mobile Server, list the requirements for a server or cluster name that you enter. However, if you do not specifically select the option to Set SAP Mobile Server name (Set SAP Mobile Server name and cluster name on first SAP Mobile Server in a cluster), the documentation does not state:</p> <ul style="list-style-type: none"> • The installer uses the computer name by default for the server name (and cluster name on the first SAP Mobile Server in a cluster). • The computer name must meet the same requirements for server and cluster names as names that you enter. <p>The requirements for server and cluster names are documented in the <i>Installation Guide for Runtime</i>, in the <i>Selecting Installation Options</i> sections of the tasks that install a new instance of SAP Mobile Server. See the step that begins, "(Optional) If you selected Set SAP Mobile Server name ..."</p> <p>If the computer name does not meet those requirements, you have two options for installing SAP Mobile Server on that system:</p> <p>Workaround 1: Keep the computer name as is. In the <i>Selecting Installation Options</i> section of the installation task, select the option to Set SAP Mobile Server name ..., and then specify a name that meets the requirements listed in the step that follows immediately after making that selection.</p> <p>Workaround 2: Before running the installer, change the computer name so that it meets all the requirements for user-entered server and cluster names. Then, in the <i>Selecting Installation Options</i> section of the installation task, do not select the option to Set SAP Mobile Server name ...</p>

Obtaining Help and Additional Information

Use the Product Documentation site and online help to learn more about this product release.

- Product Documentation at <http://sybooks.sybase.com/> – online documentation that you can access using a standard Web browser. You can browse documents online, or download them as PDFs. The Web site also has links to other resources, such as white papers, community forums, maintenance releases, and support content.
- Online help in the product, if available.

To read or print PDF documents, you need Adobe Acrobat Reader, which is available as a free download from the *Adobe* Web site.

Note: A more recent release bulletin, with critical product or document information added after the product release, may be available from the Product Documentation Web site.

Technical Support

Get support for SAP® products.

If your organization has purchased a support contract for this product, then one or more of your colleagues is designated as an authorized support contact. If you have any questions, or if you need assistance during the installation process, ask a designated person to contact Technical Support as specified in your contract:

- Sybase Technical Support or the Sybase subsidiary in your area
- SAP Technical Support

Customers with an SAP support contract can obtain support for this product at the SAP support site, <http://service.sap.com/sybase/support>. You can also find information about Sybase support migration at this location (login may be required).

Customers with a Sybase support contract can obtain support for this product at <http://www.sybase.com/support> (login required).

Downloading Product Updates

Get maintenance releases, support packages and patches, and related information.

- If you purchased the product directly from Sybase or from an authorized Sybase reseller:

- a) Go to <http://www.sybase.com/support>.
- b) Select **Support > EBFs/Maintenance**.
- c) If prompted, enter your MySybase user name and password.
- d) (Optional) Select a filter, a time frame, or both, and click **Go**.
- e) Select a product.

Padlock icons indicate that you do not have download authorization for certain EBF/Maintenance releases because you are not registered as an authorized support contact. If you have not registered, but have valid information provided by your Sybase representative or through your support contract, click **My Account** to add the “Technical Support Contact” role to your MySybase profile.

- f) Click the **Info** icon to display the EBF/Maintenance report, or click the product description to download the software.
- If you ordered your product under an SAP contract:
 - a) Go to <http://service.sap.com/swdc> and log in if prompted.
 - b) Select **Search for Software Downloads** and enter the name of your product. Click **Search**.

Accessibility Features

Accessibility ensures access to electronic information for all users, including those with disabilities.

Documentation for this product is available in an HTML version that is designed for accessibility.

Vision impaired users can navigate through the online document with an adaptive technology such as a screen reader, or view it with a screen enlarger.

HTML documentation has been tested for compliance with accessibility requirements of Section 508 of the U.S Rehabilitation Act. Documents that comply with Section 508 generally also meet non-U.S. accessibility guidelines, such as the World Wide Web Consortium (W3C) guidelines for Web sites.

Note: You may need to configure your accessibility tool for optimal use. Some screen readers pronounce text based on its case; for example, they pronounce ALL UPPERCASE TEXT as initials, and MixedCase Text as words. You might find it helpful to configure your tool to announce syntax conventions. Consult the documentation for your tool.

For information about how Sybase supports accessibility, see the Sybase Accessibility site: <http://www.sybase.com/products/accessibility>. The site includes links to information about Section 508 and W3C standards.

You may find additional information about accessibility features in the product documentation.